

KV-27XSD/KV-27XSTA/KV-27XSC/27XSTC

RM-635

RM-634

RM-635


AEP Model

KV-27XSC

Chassis No. SCC-774E-A

KV-27XSTC


Chassis No. SCC-774D-A



RX-2 CHASSIS

August, 1986


CIRCUIT BOARDS LOCATION




SPECIFICATIONS


Television system	CCIR TV standards (system B,G and H)
Colour system	PAL
Zeiton system	Two carrier system
Channel coverage	VHF channels E2-S20 UHF channels E21-E68
Programming system	30 programmes Automatic programming digital tuning
Picture tube	Approx. 68 cm (27 inches), approx. 64 cm screen measured diagonally 114-degree deflection Trinitron system
Aerial	75-ohm standard aerial socket (DIN 45325/IEC 169-2)
Audio output	10 W + 10 W (music power)
Input/output	21-pin connector in accordance with the requirements of CENELEC standard
Outputs	Audio output connector (5-pin DIN) Recording output: 1 mV rms/kilohm Line output: variable, 0-2 V rms (max.) impedance less than 1 kilohm External speaker terminals (2-pin DIN) For 8 to 16 ohm speakers Headphones jack (stereo phone jack)
Power requirements	220-240 V ac, 50 Hz
Power consumption	120Wh
Dimensions	Approx. 800 x 543 x 475 mm (w/h/d)
Weight	Approx. 52kg
Accessory supplied	Remote Commander RM-635
Optional accessory	OPK-202 SECAM adaptor OPK-303 teletext adaptor (KV-27XSC ONLY)

KV27XS-C/TC/D/XSTA
427






(KV27XSTA only)






(KV27XSTA only)




IC	IC103		IC101		102		IC102		153		IC151		105		156 155		IC
Q	104	101							174		IC152		103		154 175, 157 151, 158 152		Q
D	103 101								151 104				153 171		152 153 154		D
ADJ	RV101																ADJ
TP	TP15																TP

SCM

[SCM-KILLER, Y DRIVE, PAL-SECAM TRANSCODER] (KV27XSD only)




(KV27XSD only)



CONNECTOR	DIODE	RESISTOR
SCM-1 C-1	D1351 C-3	R1351 B-2 R1352 B-2 R1353 B-2 R1354 B-2 R1355 C-2 R1356 A-2 R1357 B-3 R1361 B-3 R1364 B-4 R1365 B-4
CAPACITOR	IC	
C1351 B-2 C1352 B-3 C1353 B-2 C1354 B-2 C1355 B-1 C1356 B-2 C1357 B-1 C1358 B-1 C1359 C-1 C1360 C-1	IC1351 B-1	
C1361 B-4 C1362 A-3 C1363 A-4 C1364 A-3 C1366 A-1 C1367 A-1 C1368 A-1 C1369 A-2 C1370 A-2 C1371 A-2	COIL	
C1372 A-2 C1373 B-2 C1374 C-4 C1375 A-1 C1376 C-3 C1378	L1351 A-2 L1352 A-4 L1353 A-1 L1354 A-2	
	TRANSISTOR	
	Q1351 C-2 Q1352 C-3 Q1354 B-4 Q1356 A-3 Q1357 B-3 Q1359 B-2 Q1360 C-3	R1367 C-3 R1368 B-3 R1371 B-3 R1372 A-3 R1373 A-1 R1374 A-1 R1375 A-3 R1380 B-3 R1382 A-3 R1383 A-3 R1384 B-2 R1385 B-3 R1386 C-3 R1387 B-3 R1388 B-3 R1389 B-1 R1390 A-2
		VARIABLE RESISTOR
		RV1351 A-2

SCM

(KV27XSTA only)





KV27XS-C/TC/D/XSTA
435


[REG OUT]

KV27XS-C/TC/D/XSTA
437

A BAND SW, QUASI ID,
SIF, VIF, AFT, MATRIX

D1 [PIN CTRL, Y BOW]






A


CONNECTOR	C135 D.2 C136 D.3 C137 B.2 C138 B.2 C139 C.2 C140 C.2 C141 D.2 C142 D.5 C143 B.5 C144 C.5	C180 D.6 C181 C.6 C182 D.7 C183 D.6 C184 D.5 C186 D.7 C188 C.3 C189 D.1	COIL	L101 B.5 L102 B.4 L103 B.4 L104 C.4 L105 D.5 L106 D.2 L107 F.3 L109 D.5 L110 D.2 L111 D.4 L113 C.1	RESISTOR	R101 B.1 R102 C.1 R105 D.3 R106 D.3 R107 C.2 R108 D.1 R109 D.1 R110 D.1 R111 B.4 R112 B.4 R113 B.4 R114 C.4 R115 D.2 R116 B.2 R117 B.2 R118 D.6 R119 D.6 R120 D.6 R122 C.2 R125 C.2 R126 D.4 R127 C.4 R129 D.4 R131 D.4 R132 D.4 R134 D.4 R135 D.4 R136 D.4 R137 D.4 R140 D.4	R152 C.5 R153 A.5 R154 C.7 R155 B.5 R156 C.5 R157 C.7 R158 C.7 R159 D.7 R160 D.7 R161 D.7 R162 D.7 R166 A.7 R167 A.7 R168 A.7 R172 D.7 R173 D.7 R174 D.7 R175 D.7 R176 D.7 R177 D.7 R178 D.7 R179 D.7 R180 D.7 R181 D.7 R182 D.7 R183 D.7 R184 D.7 R185 D.7 R188 D.7 R191 D.7 R192 D.7 R193 D.7	SAW FILTER	SWF1015
CAPACITOR	C102 A.1 C104 B.1 C105 B.1 C106 A.2 C107 B.2 C108 C.1 C109 D.2 C110 D.1 C111 D.1 C112 B.5 C113 B.5 C114 B.4 C115 B.4 C116 B.4 C117 B.3 C118 C.4 C119 B.3 C120 C.4 C122 B.5 C123 C.5 C124 D.5 C126 C.4 C127 C.4 C128 D.4 C129 C.4 C130 B.2 C131 C.3 C132 C.3 C133 D.3 C134 C.3	C145 B.6 C146 B.7 C147 B.5 C148 B.6 C149 B.5 C150 C.4 C151 A.7 C152 A.7 C153 B.7 C154 A.7 C155 A.7 C156 B.7 C157 B.7 C158 C.7 C159 B.6 C160 B.7 C164 B.6 C165 C.6 C167 C.6 C168 C.7 C169 C.6 C170 D.6 C171 D.6 C172 C.6 C173 C.7 C174 C.7 C175 C.7 C176 C.8 C177 D.8 C179 D.7	FILTER CD151 A.6 CF101 C.4 CF102 D.5 CF151 A.6 DIODE D101 C.3 D102 A.7 D103 B.1 D104 C.5 D105 B.7 D151 A.5 D152 A.8 D153 A.8 D154 A.8 D170 C.6 D171 D.7 IC IC101 C.2 IC102 C.4 IC103 B.2 IC151 B.6 IC152 C.6	TRANSISTOR	Q101 C.2 Q102 C.2 Q103 C.2 Q104 C.1 Q105 C.2 Q151 C.2 Q152 C.2 Q153 C.2 Q154 A.2 Q155 A.8 Q156 A.8 Q157 A.8 Q158 B.5 Q172 C.6 Q173 C.6 Q174 C.6 Q175 C.6	R141 C.4 R142 A.7 R143 B.2 R144 B.2 R145 B.2 R146 C.2 R151 A.5	VARIABLE RESISTOR RV101 C.4 RV151 C.2		

V


[CCT, μ -PROCESSOR] KV-27XSTC ONLY



[R.G.B OUT]

N[REMOTE CONTROL,
HEAD AMP]**H2**


[INDICATOR]



3. CHASSIS

■: TA,BV3x8

7-685-646-71



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
101	*A-1340-817-A	D1 BOARD, COMPLETE		104	*A-1346-817-31	TERMINAL BOARD ASSY, ANTENNA	
102	*A-1-237-280-11	RESISTOR ASSY, HIGH-VOLTAGE		105	*A-1345-618-A	D BOARD, SUB, COMPLETE	
103	*A-1-439-332-42	TRANSFORMER ASSY, FLYBACK					

KV27XS-C/TC/D/XSTA

444

F

NOTE:

ELECTRICAL PARTS LIST

* Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

* All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

CAPACITORS

* MF : μ F, PF : μ F

RESISTORS

* All resistors are in ohms
* F : nonflammable

COILS

* MMH : mH, UH : μ H

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
*A-1245-313-A F BOARD, SUB COMPLETE							

CAPACITOR				DIODE			
C601	1-108-745-62	MYLAR 0.22MF	20% 300V	D601	8-719-503-06	DIODE 53W602	
C602	1-108-745-62	MYLAR 0.22MF	20% 300V	D602	8-719-100-65	DIODE RD12E-82	
C603	1-162-578-51	CERAMIC 0.0047MF	20% 400V	D603	8-719-815-55	DIODE 1S1555	
C604	1-162-578-51	CERAMIC 0.0047MF	20% 400V	D604	8-759-157-40	IC UPC574J	
C605	1-162-578-51	CERAMIC 0.0047MF	20% 400V	D605	8-719-901-93	DIODE V19E	
C606	1-162-578-51	CERAMIC 0.0047MF	20% 400V	D606	8-719-815-55	DIODE 1S1555	
C607	1-161-964-61	CERAMIC 0.0047MF	250V	D607	8-719-815-55	DIODE 1S1555	
C608	1-161-964-61	CERAMIC 0.0047MF	250V	D608	8-719-815-55	DIODE 1S1555	
C609	1-161-964-61	CERAMIC 0.0047MF	250V	D609	8-719-305-15	DIODE GH3F	
C610	1-125-318-00	ELECT(BLOCK) 220MF	20% 400V	D651	8-719-928-08	DIODE ERD28-08	
C611	1-110-175-81	MYLAR 0.1MF	10% 100V	D652	8-719-901-93	DIODE V19E	
C612	1-130-022-00	FILM 0.0022MF	5% 50V	D653	8-719-901-93	DIODE V19E	
C613	1-123-356-00	ELECT 10MF	20% 16V	D654	8-719-901-93	DIODE V19E	
C614	1-123-356-00	ELECT 10MF	20% 25V	D654A	8-719-924-06	DIODE ERC24-06S	
C615	1-102-106-00	CERAMIC 100PF	10% 50V	D655	8-719-901-93	DIODE V19E	
C616	1-123-369-00	ELECT 4.7MF	20% 25V	D655A	8-719-924-06	DIODE ERC24-06S	
C617	1-110-186-81	MYLAR 0.0047MF	10% 400V	D656	8-719-901-93	DIODE V19E	
C618	1-102-030-00	CERAMIC 330PF	10% 500V	D657	8-719-901-93	DIODE V19E	
C619	1-110-182-81	MYLAR 0.022MF	10% 250V	D658	8-719-102-74	DIODE RD6.2E-W2	
C620	1-123-332-00	ELECT 47MF	20% 16V	D659	8-719-102-78	DIODE RD6.8E-W2	
C621	1-136-065-00	FILM 0.0027MF	3% 2KV	D660	8-719-815-55	DIODE 1S1555	
C622	1-123-385-00	ELECT 22MF	20% 100V	D661	8-719-815-55	DIODE 1S1555	
C623	1-161-973-00	CERAMIC 220PF	10% 400V	D663	8-719-102-74	DIODE RD6.2E-W2	
C624	1-161-973-00	CERAMIC 220PF	10% 400V	D664	8-719-100-65	DIODE RD12E-82	
C625	1-123-379-00	ELECT 0.47MF	20% 50V	CONNECTOR			
C626	1-123-381-00	ELECT 2.2MF	20% 50V	F1	*1-506-349-21	3P PLUG (L)	
C627	1-123-380-00	ELECT 1MF	20% 50V	F2	*1-508-765-00	3P PLUG (M)	
C628	1-108-618-91	MYLAR 0.0022MF	10% 100V	F3	*1-508-786-00	2P PLUG (M)	
C632	1-102-002-00	CERAMIC 680PF	10% 500V	F4	*1-508-765-00	3P PLUG (M)	
C633	1-108-745-62	MYLAR 0.22MF	20% 300V	F6	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P	
C634	1-110-175-81	MYLAR 0.1MF	10% 100V	F7	*1-564-883-11	PLUG, CONNECTOR 6P	
C651	1-102-155-00	CERAMIC 330PF	20% 2KV	FUSE			
C652	1-124-347-00	ELECT 100MF	20% 160V	F601	*A-1-532-350-11	FUSE, TIME-LAG 4A/250V	
C653	1-123-364-00	ELECT 1000MF	20% 50V		1-533-149-00	HOLDER, FUSE; F601	
C654	1-123-606-00	ELECT 1000MF	20% 25V	IC			
C655	1-123-334-00	ELECT 220MF	20% 25V	IC601	8-759-100-75	IC UPC1394C	
C656	1-102-038-00	CERAMIC 0.001MF	500V	IC602	8-719-800-82	DIODE TLP567	
C656A	1-102-038-00	CERAMIC 0.001MF	500V	IC651	8-759-145-58	IC UPC4558C	
C658	1-123-332-00	ELECT 47MF	20% 16V	COIL			
C659	1-102-112-00	CERAMIC 330PF	10% 50V	L601	1-407-365-00	COIL, CHOKE	
C660	1-123-356-00	ELECT 10MF	20% 50V	L651	1-425-613-00	COIL, AIR-CORE, OF TYPE	
C661	1-123-333-00	ELECT 100MF	20% 16V	L652	1-459-442-00	COIL (WITH CORE)	
C662	1-110-190-81	MYLAR 0.01MF	10% 400V	TRANSISTOR			
C663	1-123-380-00	ELECT 1MF	20% 50V	Q601	8-729-195-82	TRANSISTOR 2SC2958	
C664	1-123-380-00	ELECT 1MF	20% 50V	Q602	8-729-301-00	TRANSISTOR 2S01497-02	
C666	1-123-307-00	ELECT 100MF	20% 6.3V		4-365-216-00	SPACER, MICA;Q602	
C667	1-102-121-00	CERAMIC 0.0022MF	10% 50V		*A-368-683-01	SPRING;Q602	
C668	1-110-190-81	MYLAR 0.01MF	10% 400V	Q603	8-729-178-54	TRANSISTOR 2SC2785	


EXPLODED VIEWS

NOTE:

- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remark column.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.


1. CABINET



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
1	4-381-502-01	BUTTON, POWER (FOR GRAY)		10	*4-342-118-00	LID, SHIELD CASE, R	
	4-381-502-11	BUTTON, POWER (FOR BLACK)		11	*4-373-212-03	LABEL, CONTROL	
2	*4-381-501-01	HOLDER, POWER SW		12	*4-381-520-01	PANEL, CONTROL	
3	Δ1-554-762-41	SWITCH, PUSH (AC POWER)(1 KEY)		13	4-373-213-01	BUTTON, MULTI	
4	*4-373-216-01	CAP. INSULATING, POWER SWITCH		14	*1-619-358-11	H1 BOARD	
5	1-503-642-11	SPEAKER		15	4-361-938-00	PUSH BUTTON (A)	
6	4-373-234-01	CLIP		16	*1-619-359-11	H2 BOARD	
7	*4-342-117-00	CASE, SHIELD (MAIN), R		17	4-373-229-01	COVER, REAR	
8	*4-333-624-00	FILM (N), SPECIAL		18	*4-381-527-01	LABEL, COMBINATION	
9	*1-611-717-11	N BOARD		19	4-329-127-00	CLAMP, CORD	

2. CRT

▲: TA, BV4x12



No.	Part No.	Description	Remark	No.	Part No.	Description	Remark
51	X-4381-511-1	CABINET ASSY (FOR GRAY)	52-59	66	*1-618-883-11	J1 BOARD	
	X-4381-511-2	CABINET ASSY (FOR BLACK)	52-59	67	3-703-003-00	SPACER, DY	
52	X-4381-510-1	LID ASSY (FOR GRAY)		68	Δ8-736-653-05	CRT (A64JK360X)	
	X-4381-510-2	LID ASSY (FOR BLACK)		69	1-452-146-21	MAGNET, BMC	
53	X-4381-509-1	DOOR ASSY (FOR GRAY)		70	Δ1-451-255-31	DEFLECTION YOKE (SY-164)	
	X-4381-509-2	DOOR ASSY (FOR BLACK)		71	Δ1-452-391-21	NECK ASSY, CRT (NA305)	
54	X-314-871-00	CUSHION		72	*A-1330-712-A	C BOARD, COMPLETE	
55	3-703-035-11	SHAFT, LID		73	Δ1-426-278-11	COIL, DEMAGNETIZATION	
56	4-381-503-01	PLATE, K.H. (FOR GRAY)		74	4-303-774-XX	SPRING	
	4-381-503-11	PLATE, K.H. (FOR BLACK)		75	4-374-494-01	SCREW, SPECIAL	
57	4-381-511-01	PLATE (C), ORNAMENTAL (FOR GRAY)		76	*4-371-629-01	STOPPER, WIRE	
	4-381-511-11	PLATE (C), ORNAMENTAL (FOR BLACK)		77	Δ1-228-544-11	RESISTOR ASSY, HIGH-VOLTAGE	
58	4-381-512-01	PLATE (D), ORNAMENTAL (FOR GRAY)		78	*A-1296-108-A	A BOARD, SUB, COMPLETE	
	4-381-512-11	PLATE (D), ORNAMENTAL (FOR BLACK)		79	Δ1-463-577-11	TUNER, ET (BT-883A)	
59	4-374-115-01	EMBLEM, SONY		80	*A-1245-313-A	F BOARD, SUB, COMPLETE	
60	X-4381-506-1	PLATE ASSY, IR(FOR GRAY)(KV-27XSC ONLY)		81	*4-375-709-01	COVER, FUSE	
	X-4381-506-2	PLATE ASSY, IR(FOR BLACK)(KV-27XSC ONLY)		82	Δ4-022-115-01	HOLDER, AC CORD	
	X-4381-508-1	PLATE ASSY, IR(FOR GRAY)(KV-27XSTC ONLY)		83	Δ1-551-270-11	CORD, POWER	
	X-4381-508-2	PLATE ASSY, IR(FOR BLACK)(KV-27XSTC ONLY)		84	4-308-870-00	CLIP, LEAD WIRE	
61	4-381-515-01	WINDOW, ORNAMENTAL		85	1-452-032-00	MAGNET, DISK; 10MM Φ	
62	4-381-514-01	PLATE, Z1 (FOR GRAY)		86	1-452-094-00	MAGNET, ROTATABLE DISK; 15MM Φ	
	4-381-514-11	PLATE, Z1 (FOR BLACK)		87	X-4308-015-0	PERMALLOY ASSY, CONVERGENCE	
63	4-373-234-01	CLIP		88	*A-1325-025-A	V BOARD, COMPLETE (KV-27XSTC ONLY)	
64	*4-373-228-01	HOLDER (C) (LEFT)					
65	*4-373-227-01	HOLDER (C) (RIGHT)					

(KV27XSTA only)

79 Δ1-463-411-21 TUNER, ET UHF/VHF ET (UV411/CEI)

KV27XS-C/TC/D/XSTA
443

A

A V

Ref.No.	Part No.	Description	Remark
<u>IC</u>			
IC101	8-759-909-08	IC TDA3541	
IC102	8-759-909-54	IC TDA2546A	
IC103	8-759-602-16	IC M54572L	
IC151	8-759-007-54	IC TDA4940	
IC152	8-759-007-55	IC TDA4944	
<u>COIL</u>			
L101	1-404-476-00	COIL, IF	
L102	1-404-476-00	COIL, IF	
L103	1-408-432-31	MICRO INDUCTOR 1.5UH	
L104	1-408-406-00	MICRO INDUCTOR 5.6UH	
L105	1-404-477-00	COIL, IF	
L106	1-404-493-00	COIL	
L107	1-404-493-00	COIL	
L109	1-408-409-00	MICRO INDUCTOR 10UH	
L110	1-408-406-00	MICRO INDUCTOR 5.6UH	
L111	1-404-493-00	COIL	
L113	1-408-226-00	MICRO INDUCTOR 82UH	
L114	1-407-489-00	MICRO INDUCTOR 560UH	
L116	1-408-406-00	MICRO INDUCTOR 5.6UH	
L117	1-408-428-00	MICRO INDUCTOR 390UH	
L170	1-408-247-00	MICRO INDUCTOR 33MMH	
L171	1-408-408-00	MICRO INDUCTOR 8.2UH	
<u>TRANSISTOR</u>			
Q101	8-729-178-54	TRANSISTOR 2SC2785	
Q102	8-729-105-47	TRANSISTOR 2SC2026-L	
Q103	8-729-117-54	TRANSISTOR 2SA1175	
Q104	8-729-900-36	TRANSISTOR DTC124ES	
Q105	8-729-117-54	TRANSISTOR 2SA1175	
Q151	8-729-178-54	TRANSISTOR 2SC2785	
Q152	8-729-178-54	TRANSISTOR 2SC2785	
Q153	8-729-178-54	TRANSISTOR 2SC2785	
Q154	8-729-900-89	TRANSISTOR DTC144ES	
Q155	8-729-178-54	TRANSISTOR 2SC2785	
Q156	8-729-178-54	TRANSISTOR 2SC2785	
Q157	8-729-900-89	TRANSISTOR DTC144ES	
Q158	8-729-900-89	TRANSISTOR DTC144ES	
Q172	8-729-117-54	TRANSISTOR 2SA1175	
Q173	8-729-178-54	TRANSISTOR 2SC2785	
Q174	8-729-178-54	TRANSISTOR 2SC2785	
Q175	8-729-178-54	TRANSISTOR 2SC2785	
<u>RESISTOR</u>			
R101	1-215-738-91	METAL 1K 5% 1/6W	
R102	1-215-738-91	METAL 1K 5% 1/6W	
R105	1-215-760-91	METAL 8.2K 5% 1/6W	
R106	1-215-750-91	METAL 3.3K 5% 1/6W	
R107	1-215-750-91	METAL 3.3K 5% 1/6W	
R108	1-215-798-91	METAL 330K 5% 1/6W	
R109	1-215-746-91	METAL 2.2K 5% 1/6W	

Ref.No.	Part No.	Description	Remark
R110	1-215-746-91	METAL 2.2K 5% 1/6W	
R111	1-215-754-91	METAL 4.7K 5% 1/6W	
R112	1-215-734-91	METAL 680 5% 1/6W	
R113	1-215-752-91	METAL 3.9K 5% 1/6W	
R114	1-215-722-91	METAL 220 5% 1/6W	
R115	1-215-750-91	METAL 3.3K 5% 1/6W	
R116	1-215-730-91	METAL 470 5% 1/6W	
R117	1-215-710-91	METAL 68 5% 1/6W	
R118	1-215-724-91	METAL 270 5% 1/6W	
R119	1-215-730-91	METAL 470 5% 1/6W	
R120	1-215-778-91	METAL 47K 5% 1/6W	
R122	1-215-762-91	METAL 10K 5% 1/6W	
R125	1-215-736-91	METAL 820 5% 1/6W	
R126	1-215-736-91	METAL 820 5% 1/6W	
R127	1-215-736-91	METAL 820 5% 1/6W	
R129	1-215-810-91	METAL 1M 5% 1/6W	
R131	1-215-778-91	METAL 47K 5% 1/6W	
R132	1-215-762-91	METAL 10K 5% 1/6W	
R134	1-215-782-91	METAL 68K 5% 1/6W	
R135	1-215-776-91	METAL 39K 5% 1/6W	
R136	1-215-770-91	METAL 22K 5% 1/6W	
R137	1-215-770-91	METAL 22K 5% 1/6W	
R140	1-215-738-91	METAL 1K 5% 1/6W	
R141	1-215-766-91	METAL 15K 5% 1/6W	
R142	1-215-786-91	METAL 100K 5% 1/6W	
R143	1-215-786-91	METAL 100K 5% 1/6W	
R144	1-215-752-91	METAL 3.9K 5% 1/6W	
R145	1-215-752-91	METAL 3.9K 5% 1/6W	
R146	1-215-754-91	METAL 4.7K 5% 1/6W	
R151	1-215-736-91	METAL 820 5% 1/6W	
R152	1-215-776-91	METAL 39K 5% 1/6W	
R153	1-215-728-91	METAL 390 5% 1/6W	
R154	1-215-714-91	METAL 100 5% 1/6W	
R155	1-215-770-91	METAL 22K 5% 1/6W	
R156	1-215-784-91	METAL 82K 5% 1/6W	
R157	1-215-754-91	METAL 4.7K 5% 1/6W	
R158	1-215-754-91	METAL 4.7K 5% 1/6W	
R159	1-215-754-91	METAL 4.7K 5% 1/6W	
R160	1-215-754-91	METAL 4.7K 5% 1/6W	
R161	1-215-738-91	METAL 1K 5% 1/6W	
R162	1-215-738-91	METAL 1K 5% 1/6W	
R166	1-215-750-91	METAL 3.3K 5% 1/6W	
R167	1-215-774-91	METAL 33K 5% 1/6W	
R168	1-215-770-91	METAL 22K 5% 1/6W	
R172	1-215-720-91	METAL 180 5% 1/6W	
R173	1-215-778-91	METAL 47K 5% 1/6W	
R174	1-215-796-91	METAL 270K 5% 1/6W	
R175	1-215-772-91	METAL 27K 5% 1/6W	
R176	1-215-738-91	METAL 1K 5% 1/6W	
R177	1-215-762-91	METAL 10K 5% 1/6W	
R178	1-215-762-91	METAL 10K 5% 1/6W	
R179	1-215-762-91	METAL 10K 5% 1/6W	
R180	1-215-738-91	METAL 1K 5% 1/6W	

Ref.No.	Part No.	Description	Remark
R181	1-215-740-91	METAL 1.2K 5% 1/6W	
R182	1-215-746-91	METAL 2.2K 5% 1/6W	
R183	1-215-738-91	METAL 1K 5% 1/6W	
R184	1-215-724-91	METAL 270 5% 1/6W	
R185	1-215-726-91	METAL 330 5% 1/6W	
R188	1-215-766-91	METAL 15K 5% 1/6W	
R191	1-215-732-91	METAL 560 5% 1/6W	
R192	1-215-732-91	METAL 560 5% 1/6W	
R193	1-215-714-91	METAL 100 5% 1/6W	
<u>VARIABLE RESISTOR</u>			
RV101	1-228-727-00	RES, ADJ, CERAMIC CARBON 47K	
RV151	1-228-726-00	RES, ADJ, CERAMIC CARBON 33K	
<u>TUNER</u>			
TU101	1-463-577-11	TUNER, ET (BT-883A)	

*A-1325-025-A V BOARD, COMPLETE (KV-27XSTC OM.Y)			

*4-371-102-01 CASE (MAIN), SHIELD, A1			
*4-371-103-01 CASE (UPPER LID), SHIELD, A1			
*4-371-104-01 CASE (BOTTOM LID), SHIELD, A1			
<u>CAPACITOR</u>			
C001	1-123-307-00	ELECT 100MF 20% 10V	
C002	1-123-332-00	ELECT 47MF 20% 16V	
C003	1-123-309-00	ELECT 330MF 20% 6.3V	
C004	1-123-332-00	ELECT 47MF 20% 16V	
C005	1-123-308-00	ELECT 220MF 20% 6.3V	
C006	1-123-321-00	ELECT 220MF 20% 16V	
C007	1-110-175-81	MYLAR 0.1MF 10% 100V	
C008	1-102-951-00	CERAMIC 15PF 5% 50V	
C009	1-102-074-00	CERAMIC 0.001MF 10% 50V	
C010	1-102-824-00	CERAMIC 470PF 5% 50V	
C011	1-110-182-81	MYLAR 0.022MF 10% 250V	
C012	1-102-980-00	CERAMIC 270PF 5% 50V	
C013	1-102-973-00	CERAMIC 100PF 5% 50V	
C014	1-102-851-00	CERAMIC 15PF 5% 50V	
C015	1-102-883-00	CERAMIC 27PF 5% 50V	
C016	1-110-190-81	MYLAR 0.01MF 10% 400V	
C017	1-110-171-81	MYLAR 0.047MF 10% 100V	
C018	1-102-953-00	CERAMIC 18PF 5% 50V	
C019	1-110-171-81	MYLAR 0.047MF 10% 100V	
C020	1-102-978-00	CERAMIC 220PF 5% 50V	
C021	1-110-173-81	MYLAR 0.068MF 10% 100V	
C022	1-102-963-00	CERAMIC 33PF 5% 50V	
C023	1-102-963-00	CERAMIC 33PF 5% 50V	
C024	1-136-177-00	FILM 1MF 5% 50V	
C025	1-123-298-00	ELECT 470MF 20% 6.3V	
C026	1-102-973-00	CERAMIC 100PF 5% 50V	
C037	1-110-175-81	MYLAR 0.1MF 10% 100V	

Ref.No.	Part No.	Description	Remark
C040	1-136-177-00	FILM 1MF 5% 50V	
C041	1-110-175-81	MYLAR 0.1MF 10% 100V	
C042	1-102-820-00	CERAMIC 330PF 5% 50V	
C043	1-123-308-00	ELECT 220MF 20% 6.3V	
C044	1-110-175-81	MYLAR 0.1MF 10% 100V	
C045	1-102-116-00	CERAMIC 680PF 10% 50V	
C046	1-123-356-00	ELECT 10MF 20% 16V	
C049	1-101-361-00	CERAMIC 150PF 10% 50V	
C050	1-101-361-00	CERAMIC 150PF 10% 50V	
<u>TRIMMER</u>			
CT001	1-141-181-11	CAP, TRIMMER	
<u>DIODE</u>			
D001	8-719-911-19	DIODE 1SS119	
D002	8-719-100-35	DIODE RD5.6E-B2	
D003	8-719-100-68	DIODE RD13E-B2	
D004	8-719-101-41	DIODE RD3.9E-L2	
D005	8-719-109-88	DIODE RD5.6ES-B1	
D006	8-719-911-19	DIODE 1SS119	
D007	8-719-911-19	DIODE 1SS119	
D008	8-719-911-19	DIODE 1SS119	
D011	8-719-911-19	DIODE 1SS119	
D012	8-719-911-19	DIODE 1SS119	
D013	8-719-109-88	DIODE RD5.6ES-B1	
<u>IC</u>			
IC001	8-759-918-54	IC SAA5230	
IC002	8-759-918-56	IC SAA5240A	
*1-526-722-00 SOCKET, IC 40P; IC002			
IC003	8-759-206-27	IC TC5564PL-15	
IC004	8-759-108-76	IC CX526-050	
<u>COIL</u>			
L001	1-408-411-00	MICRO INDUCTOR 15UH	
<u>TRANSISTOR</u>			
Q001	8-729-109-53	TRANSISTOR 2SD795A	
Q002	8-729-178-54	TRANSISTOR 2SC2785	
Q003	8-729-177-43	TRANSISTOR 2SD774	
Q004	8-729-117-54	TRANSISTOR 2SA1175	
Q005	8-729-900-89	TRANSISTOR DTC144ES	
Q006	8-729-117-54	TRANSISTOR 2SA1175	
Q007	8-729-178-54	TRANSISTOR 2SC2785	
Q008	8-729-178-54	TRANSISTOR 2SC2785	
Q009	8-729-900-89	TRANSISTOR DTC144ES	
Q010	8-729-117-54	TRANSISTOR 2SA1175	
Q011	8-729-117-54	TRANSISTOR 2SA1175	
Q012	8-729-117-54	TRANSISTOR 2SA1175	

A

445

C D1

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
5G703	1-519-063-XX	DISCHARGING GAP		<u>TRANSISTOR</u>			
*****				Q1501	8-729-178-54	TRANSISTOR 2SC2785	
*A-1340-817-A D1 BOARD, COMPLETE				Q1502	8-729-178-54	TRANSISTOR 2SC2785	
*****				Q1503	8-729-374-02	TRANSISTOR 2SB740	
				Q1504	8-729-195-82	TRANSISTOR 2SC2958	
<u>CAPACITOR</u>				<u>RESISTOR</u>			
C1501	1-108-630-91	MYLAR 0.022MF	10% 100V	R1501	1-247-805-00	CARBON 82 5% 1/6W	
C1503	1-106-196-00	MYLAR 0.01MF	10% 100V	R1502	1-247-145-00	CARBON 3.9K 5% 1/4W	
C1504	1-123-380-00	ELECT 1MF	20% 50V	R1503	1-249-415-11	CARBON 680 5% 1/6W	
C1505	1-108-622-91	MYLAR 0.0047MF	10% 100V	R1504	1-249-432-11	CARBON 18K 5% 1/6W	
C1506	1-123-382-00	ELECT 3.3MF	20% 50V	R1505	1-249-423-11	CARBON 3.3K 5% 1/6W	
C1507	1-123-357-00	ELECT 22MF	20% 50V	R1506	1-249-432-11	CARBON 18K 5% 1/6W	
C1508	1-123-379-00	ELECT 0.47MF	20% 50V	R1508	1-249-432-11	CARBON 18K 5% 1/6W	
C1509	1-123-360-00	ELECT 100MF	20% 50V	R1509	1-247-702-11	CARBON 150 5% 1/4W	
C1510	1-123-381-00	ELECT 2.2MF	20% 50V	R1510	1-249-417-11	CARBON 1K 5% 1/6W	
C1511	1-123-380-00	ELECT 1MF	20% 50V	R1511	1-246-533-00	CARBON 330K 5% 1/4W	
C1512	1-106-196-00	MYLAR 0.01MF	10% 100V	R1512	1-247-891-00	CARBON 330K 5% 1/6W	
C1513	1-123-332-00	ELECT 47MF	20% 16V	R1513	1-247-829-00	CARBON 820 5% 1/6W	
C1514	1-123-330-00	ELECT 22MF	20% 16V	R1514	1-247-815-00	CARBON 220 5% 1/6W	
C1515	1-123-330-00	ELECT 22MF	20% 16V	R1515	1-246-535-00	CARBON 390K 5% 1/4W	
C1516	1-123-360-00	ELECT 100MF	20% 50V	R1516	1-249-429-11	CARBON 10K 5% 1/6W	
C1517	1-123-382-00	ELECT 3.3MF	20% 50V	R1517	1-247-721-11	CARBON 4.7K 5% 1/4W	
C1518	1-106-192-00	MYLAR 0.0068MF	10% 100V	R1518	1-249-465-11	CARBON 4.7K 5% 1/4W	
C1519	1-106-208-00	MYLAR 0.033MF	10% 100V	R1519	1-249-419-11	CARBON 1.5K 5% 1/6W	
C1520	1-123-333-00	ELECT 100MF	20% 16V	R1520	1-247-839-00	CARBON 2.2K 5% 1/6W	
C1521	1-108-637-00	MYLAR 0.082MF	10% 100V	R1521	1-249-435-11	CARBON 33K 5% 1/6W	
C1522	1-108-630-91	MYLAR 0.022MF	10% 100V	R1522	1-249-435-11	CARBON 33K 5% 1/6W	
C1523	1-123-356-00	ELECT 10MF	20% 16V	R1523	1-247-853-00	CARBON 8.2K 5% 1/6W	
C1524	1-108-622-91	MYLAR 0.0047MF	10% 100V	R1524	1-247-811-00	CARBON 150 5% 1/6W	
C1525	1-129-701-00	FILM 0.01MF	5% 100V	R1525	1-249-429-11	CARBON 10K 5% 1/6W	
C1526	1-102-125-00	CERAMIC 0.0047MF	10% 50V	R1526	1-247-725-11	CARBON 10K 5% 1/4W	
C1527	1-136-165-00	FILM 0.1MF	5% 50V	R1527	1-247-787-00	CARBON 15 5% 1/6W	
<u>CONNECTOR</u>				R1528	1-249-414-11	CARBON 560 5% 1/6W	
CNJ1	*1-562-370-21	CONNECTOR, BOARD TO BOARD 18P		R1529	1-249-434-11	CARBON 27K 5% 1/6W	
<u>DIODE</u>				R1530	1-216-451-11	METAL OXIDE 120 5% 2W	F
D1501	8-719-911-19	DIODE 1SS119		R1531	1-215-865-11	METAL OXIDE 220 5% 1W	F
D1502	8-719-911-19	DIODE 1SS119		R1532	1-247-809-00	CARBON 120 5% 1/6W	
<u>IC</u>				R1533	1-247-242-00	CARBON 1.2K 5% 1/2W	
IC1501	8-759-905-39	IC TDA1082		R1534	1-247-803-00	CARBON 68 5% 1/6W	
<u>COIL</u>				R1535	1-216-423-11	METAL OXIDE 27 5% 1W	F
L1501	1-408-245-00	MICRO INDUCTOR 22MMH		R1536	1-247-869-00	CARBON 3K 5% 1/6W	
L1502	1-407-509-00	MICRO INDUCTOR 27MMH		<u>VARIABLE RESISTOR</u>			
L1503	1-408-242-00	MICRO INDUCTOR 10MMH		RV1501	1-230-625-11	RES, ADJ, CARBON 330	
L1504	1-408-247-00	MICRO INDUCTOR 33MMH		RV1502	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1503	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1504	1-226-771-00	RES, ADJ, METAL GLAZE 1K	
				RV1505	1-230-628-11	RES, ADJ, CARBON 2.2K	
				RV1506	1-230-634-51	RES, ADJ, CARBON 100K	
				RV1507	1-230-630-11	RES, ADJ, CARBON 10K	
				RV1508	1-230-627-11	RES, ADJ, CARBON 1K	
				RV1509	1-230-271-00	RES, ADJ, CARBON 4.7K	

D1 D

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
RV1510	1-230-630-11	RES, ADJ, CARBON 10K		C219	1-123-330-00	ELECT 10MF	20% 16V
RV1511	1-230-625-11	RES, ADJ, CARBON 330		C220	1-106-212-00	MYLAR 0.047MF	10% 100V
				C221	1-108-614-91	MYLAR 0.001MF	10% 100V
<u>THERMISTOR</u>				C222	1-123-322-00	ELECT 330MF	20% 16V
TH1501	1-806-110-00	THERMISTOR		C223	1-123-380-00	ELECT 1MF	20% 50V
TH1502	1-800-625-00	THERMISTOR		C224	1-123-380-00	ELECT 1MF	20% 50V
*****				C225	1-106-322-00	MYLAR 330MF	20% 16V
A-1345-618-A D BOARD, SUB COMPLETE				C226	1-123-330-00	ELECT 22MF	20% 16V
*****				C227	1-123-330-00	ELECT 22MF	20% 16V
4-303-483-00 HEAD, WASHER, TAPPING SCREW				C228	1-102-945-00	CERAMIC 8PF	1PF 50V
<u>CAPACITOR</u>				C229	1-102-108-00	CERAMIC 150PF	10% 50V
C001	1-123-307-00	ELECT 100MF	20% 10V	C230	1-106-208-00	MYLAR 0.033MF	10% 100V
C002	1-123-381-00	ELECT 2.2MF	20% 50V	C231	1-123-333-00	ELECT 100MF	20% 16V
C003	1-102-973-00	CERAMIC 100PF	5% 50V	C232	1-123-330-00	ELECT 22MF	20% 16V
C004	1-108-603-00	MYLAR 0.1MF	5% 50V	C233	1-102-114-00	CERAMIC 470PF	10% 50V
C005	1-123-356-00	ELECT 10MF	20% 50V	C234	1-123-379-00	ELECT 0.47MF	20% 50V
C006	1-102-959-00	CERAMIC 22PF	5% 50V	C235	1-123-330-00	ELECT 22MF	20% 16V
C007	1-102-963-00	CERAMIC 33PF	5% 50V	C236	1-102-114-00	CERAMIC 470PF	10% 50V
C008	1-123-356-00	ELECT 10MF	20% 50V	C237	1-123-379-00	ELECT 0.47MF	20% 50V
C009	1-102-114-00	CERAMIC 470PF	10% 50V	C238	1-108-603-00	MYLAR 0.1MF	5% 50V
C010	1-123-369-00	ELECT 4.7MF	20% 25V	C239	1-108-603-00	MYLAR 0.1MF	5% 50V
C011	1-124-253-00	ELECT 0.47MF	20% 50V	C240	1-108-603-00	MYLAR 0.1MF	5% 50V
C012	1-101-004-00	CERAMIC 0.01MF	20% 50V	C241	1-124-472-11	ELECT 470MF	20% 10V
C015	1-123-381-00	ELECT 2.2MF	20% 50V	C243	1-123-332-00	ELECT 47MF	20% 16V
C016	1-101-810-00	CERAMIC 100PF	5% 500V	C244	1-102-114-00	CERAMIC 470PF	10% 50V
C017	1-123-306-00	ELECT 47MF	20% 10V	C245	1-102-114-00	CERAMIC 470PF	10% 50V
C017A	1-123-307-00	ELECT 100MF	20% 10V	C272	1-108-603-00	MYLAR 0.1MF	5% 50V
C018	1-106-220-00	MYLAR 0.1MF	10% 100V	C273	1-123-359-00	ELECT 47MF	20% 50V
C019	1-123-306-00	ELECT 47MF	20% 10V	C274	1-123-364-00	ELECT 1000MF	20% 50V
C020	1-102-112-00	CERAMIC 330PF	10% 50V	C276	1-123-359-00	ELECT 47MF	20% 50V
C022	1-161-377-00	CERAMIC 0.0047MF	20% 50V	C277	1-108-603-00	MYLAR 0.1MF	5% 50V
C026	1-102-074-00	CERAMIC 0.001MF	10% 50V	C278	1-123-349-00	ELECT 1000MF	20% 35V
C027	1-123-307-00	ELECT 100MF	20% 10V	C279	1-123-343-00	ELECT 33MF	20% 25V
C201	1-102-114-00	CERAMIC 470PF	10% 50V	C280	1-123-349-00	ELECT 1000MF	20% 35V
C202	1-102-074-00	CERAMIC 0.001MF	10% 50V	C281	1-123-360-00	ELECT 100MF	20% 50V
C203	1-123-380-00	ELECT 1MF	20% 50V	C282	1-101-005-00	CERAMIC 0.022MF	50V
C204	1-102-114-00	CERAMIC 470PF	10% 50V	C283	1-101-005-00	CERAMIC 0.022MF	50V
C205	1-123-356-00	ELECT 10MF	20% 16V	C284	1-102-106-00	CERAMIC 100PF	10% 50V
C206	1-102-074-00	CERAMIC 0.001MF	10% 50V	C285	1-102-106-00	CERAMIC 100PF	10% 50V
C207	1-123-380-00	ELECT 1MF	20% 50V	C288	1-108-630-91	MYLAR 0.022MF	10% 100V
C208	1-123-332-00	ELECT 47MF	20% 16V	C289	1-108-630-91	MYLAR 0.022MF	10% 100V
C209	1-106-212-00	MYLAR 0.047MF	10% 100V	C290	1-123-343-00	ELECT 33MF	20% 25V
C210	1-108-614-91	MYLAR 0.001MF	10% 100V	C291	1-123-343-00	ELECT 33MF	20% 25V
C211	1-123-380-00	ELECT 1MF	20% 50V	C301	1-102-944-00	CERAMIC 7PF	1PF 50V
C212	1-123-369-00	ELECT 4.7MF	20% 50V	C302	1-102-944-00	CERAMIC 7PF	1PF 50V
C213	1-123-356-00	ELECT 10MF	20% 16V	C303	1-102-951-00	CERAMIC 15PF	5% 50V
C214	1-123-356-00	ELECT 10MF	20% 16V	C304	1-102-816-00	CERAMIC 120PF	5% 50V
C215	1-123-356-00	ELECT 10MF	20% 16V	C308	1-123-356-00	ELECT 10MF	20% 16V
C216	1-123-356-00	ELECT 10MF	20% 16V	C309	1-123-380-00	ELECT 1MF	20% 50V
C217	1-102-074-00	CERAMIC 0.001MF	10% 50V	C311	1-123-323-00	ELECT 470MF	20% 16V
C218	1-106-208-00	MYLAR 0.033MF	10% 100V	C312	1-123-279-00	ELECT 2.2MF	20% 50V
				C313	1-123-356-00	ELECT 10MF	20% 25V
				C314	1-123-381-00	ELECT 2.2MF	20% 50V



Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
RESISTOR				CRYSTAL			
R001	1-215-867-00	METAL OXIDE 470 5% 1W F		X001	1-567-162-00	OSCILLATOR, CRYSTAL	
R002	1-215-762-91	METAL 10K 5% 1/6W		X002	1-567-495-11	OSCILLATOR, CRYSTAL	
R003	1-215-778-91	METAL 47K 5% 1/6W		X003	1-567-192-11	OSCILLATOR, CERAMIC	
R004	1-247-745-11	CARBON 330 5% 1/2W		*****			
R005	1-215-736-91	METAL 820 5% 1/6W		*A-1330-712-A C BOARD, COMPLETE			
R006	1-215-754-91	METAL 4.7K 5% 1/6W		*****			
R007	1-215-726-91	METAL 330 5% 1/6W		A1-526-644-41 SOCKET, CRT			
R008	1-215-780-91	METAL 56K 5% 1/6W		CONNECTOR			
R009	1-215-738-91	METAL 1K 5% 1/6W		C1	*1-508-765-00	3P PLUG (M)	
R010	1-215-770-91	METAL 22K 5% 1/6W		C2	*1-564-879-31	PLUG, CONNECTOR 2P	
R011	1-215-738-91	METAL 1K 5% 1/6W		C3	*1-564-880-31	PLUG, CONNECTOR 3P	
R012	1-215-762-91	METAL 10K 5% 1/6W		C4	*1-564-884-31	PLUG, CONNECTOR 7P	
R013	1-215-738-91	METAL 1K 5% 1/6W		C5	*1-508-766-00	4P PLUG (M)	
R014	1-215-738-91	METAL 1K 5% 1/6W		C6	*1-508-784-00	1P PLUG	
R015	1-215-738-91	METAL 1K 5% 1/6W		CAPACITOR			
R016	1-215-132-00	METAL 150 5% 1/4W		C701	1-102-116-00	CERAMIC 680PF 10% 50V	
R017	1-215-132-00	METAL 150 5% 1/4W		C702	1-102-116-00	CERAMIC 680PF 10% 50V	
R018	1-215-132-00	METAL 150 5% 1/4W		C703	1-102-116-00	CERAMIC 680PF 10% 50V	
R019	1-215-132-00	METAL 150 5% 1/4W		C704	1-102-945-00	CERAMIC 8PF 1PF 50V	
R020	1-215-716-91	METAL 120 5% 1/6W		C705	1-102-945-00	CERAMIC 8PF 1PF 50V	
R021	1-215-716-91	METAL 120 5% 1/6W		C706	1-102-945-00	CERAMIC 8PF 1PF 50V	
R022	1-215-716-91	METAL 120 5% 1/6W		C709	1-123-356-00	ELECT 10MF 20% 16V	
R023	1-215-776-91	METAL 39K 5% 1/6W		C711	1-102-963-00	CERAMIC 33PF 5% 50V	
R024	1-215-756-91	METAL 5.6K 5% 1/6W		C712	1-102-963-00	CERAMIC 33PF 5% 50V	
R025	1-215-746-91	METAL 2.2K 5% 1/6W		C713	1-102-963-00	CERAMIC 33PF 5% 50V	
R040	1-215-714-91	METAL 100 5% 1/6W		C731	1-123-356-00	ELECT 10MF 20% 16V	
R044	1-217-376-00	FUSIBLE 1.2 5% 1/4W F		C732	1-101-006-00	CERAMIC 0.047MF 50V	
R046	1-215-726-91	METAL 330 5% 1/6W		C733	1-123-356-00	ELECT 10MF 20% 25V	
R047	1-215-762-91	METAL 10K 5% 1/6W		C735	1-123-356-00	ELECT 10MF 20% 25V	
R048	1-215-764-91	METAL 12K 5% 1/6W		C737	1-123-254-00	ELECT 10MF 250V	
R049	1-215-690-91	METAL 10 5% 1/6W		C741	1-129-714-00	FILM 0.01MF 10% 630V	
R065	1-215-738-91	METAL 1K 5% 1/6W		C742	1-102-249-00	CERAMIC 680PF 20% 2KV	
VARIABLE RESISTOR				C751	1-101-361-00	CERAMIC 150PF 5% 50V	
RV001	1-230-631-11	RES, ADJ, CARBON 22K		C752	1-108-617-91	MYLAR 0.0018MF 10% 100V	
RV002	1-224-247-XX	RES, ADJ, METAL GLAZE 100		C753	1-106-196-00	MYLAR 0.01MF 10% 100V	
CONNECTOR				C754	1-102-98C-00	CERAMIC 270PF 5% 50V	
V1	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C757	1-106-22C-00	MYLAR 0.1MF 10% 100V	
V2	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C759	1-123-356-00	ELECT 10MF 20% 50V	
V4	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C760	1-123-38C-00	ELECT 33MF 20% 50V	
V5	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)		C761	1-101-006-00	CERAMIC 0.047MF 50V	
V6	*1-508-784-00	1P PLUG		C762	1-106-196-00	MYLAR 0.01MF 10% 100V	
V9	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		DIODE			
V10	*1-508-784-00	1P PLUG		D701	8-719-911-19	DIODE 1SS119	
V11	*1-560-124-00	PLUG, CONNECTOR (2.5MM) 4P		D702	8-719-911-19	DIODE 1SS119	
V12	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P		D703	8-719-911-19	DIODE 1SS119	
V13	*1-560-127-00	PLUG, CONNECTOR (2.5MM) 7P		D704	8-719-911-19	DIODE 1SS119	

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
D705	8-719-911-19	DIODE 1SS119		R721	1-249-420-11	CARBON 1.8K 5% 1/6W	
D706	8-719-911-19	DIODE 1SS119		R722	1-249-419-11	CARBON 1.5K 5% 1/6W	
D707	8-719-911-19	DIODE 1SS119		R723	1-249-419-11	CARBON 1.5K 5% 1/6W	
D708	8-719-911-19	DIODE 1SS119		R724	1-249-419-11	CARBON 1.5K 5% 1/6W	
D709	8-719-911-19	DIODE 1SS119		R725	1-214-961-00	METAL 750K 1% 1/4W	
COIL				R726	1-214-956-00	METAL 470K 1% 1/4W	
L701	1-408-420-00	MICRO INDUCTOR 82UH		R727	1-214-787-00	METAL 270K 1% 1/4W	
L751	1-408-413-00	MICRO INDUCTOR 22UH		R730	1-247-815-00	CARBON 220 5% 1/6W	
TRANSISTOR				R731	1-247-851-00	CARBON 6.8K 5% 1/6W	
Q701	8-729-255-12	TRANSISTOR 2SC2551		R732	1-249-420-11	CARBON 1.8K 5% 1/6W	
Q702	8-729-255-12	TRANSISTOR 2SC2551		R733	1-247-236-00	CARBON 680 5% 1/2W	
Q703	8-729-255-12	TRANSISTOR 2SC2551		R734	1-247-839-00	CARBON 2.2K 5% 1/6W	
Q704	8-729-326-11	TRANSISTOR 2SC2611		R735	1-247-799-00	CARBON 47 5% 1/6W	
	4-303-483-00	HEAD, WASHER, TAPPING SCREW;Q704		R736	1-249-417-11	CARBON 1K 5% 1/6W	
Q705	8-729-326-11	TRANSISTOR 2SC2611		R737	1-215-878-00	METAL OXIDE 33K 5% 1W F	
	4-303-483-00	HEAD, WASHER, TAPPING SCREW;Q705		R738	1-215-878-00	METAL OXIDE 33K 5% 1W F	
Q706	8-729-326-11	TRANSISTOR 2SC2611		R739	1-215-878-00	METAL OXIDE 33K 5% 1W F	
	4-303-483-00	HEAD, WASHER, TAPPING SCREW;Q706		R740	1-249-405-11	CARBON 100 5% 1/6W F	
Q707	8-729-200-17	TRANSISTOR 2SA1091		R741	1-207-458-00	WIREWOUND 0.39 10% 1/2W	
Q708	8-729-200-17	TRANSISTOR 2SA1091		R742	1-202-838-00	SOL ID 100K 10% 1/2W	
Q709	8-729-200-17	TRANSISTOR 2SA1091		R743	1-249-429-11	CARBON 10K 5% 1/6W	
Q710	8-729-802-47	TRANSISTOR 2SC3504		R744	1-202-844-00	SOL ID 330K 10% 1/2W	
Q711	8-729-802-47	TRANSISTOR 2SC3504		R745	1-202-842-91	SOL ID 220K 10% 1/2W	
Q712	8-729-802-47	TRANSISTOR 2SC3504		R746	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q713	8-729-117-54	TRANSISTOR 2SA1175		R747	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q714	8-729-900-36	TRANSISTOR DTC124ES		R748	1-202-821-11	SOL ID 1.8K 10% 1/2W	
Q715	8-729-178-54	TRANSISTOR 2SC2785		R751	1-247-833-00	CARBON 1.2K 5% 1/6W	
Q751	8-729-178-54	TRANSISTOR 2SC2785		R752	1-247-849-00	CARBON 5.6K 5% 1/6W	
Q752	8-729-178-54	TRANSISTOR 2SC2785		R753	1-249-414-11	CARBON 560 5% 1/6W	
Q753	8-729-103-43	TRANSISTOR 2S8734		R754	1-249-434-11	CARBON 27K 5% 1/6W	
Q754	8-729-177-43	TRANSISTOR 2SD0774		R755	1-249-405-11	CARBON 100 5% 1/6W	
RESISTOR				R756	1-249-419-11	CARBON 1.5K 5% 1/6W	
R701	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R757	1-249-405-11	CARBON 100 5% 1/6W	
R702	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R758	1-247-815-00	CARBON 220 5% 1/6W	
R703	1-216-485-11	METAL OXIDE 5.6K 5% 3W F		R760	1-247-819-00	CARBON 330 5% 1/6W	
R704	1-247-710-11	CARBON 560 5% 1/4W F		R761	1-249-429-11	CARBON 10K 5% 1/6W	
R705	1-247-710-11	CARBON 560 5% 1/4W F		R762	1-247-895-00	CARBON 470K 5% 1/6W	
R706	1-247-710-11	CARBON 560 5% 1/4W F		R763	1-249-429-11	CARBON 10K 5% 1/6W	
R707	1-249-417-11	CARBON 1K 5% 1/6W		R764	1-249-455-11	CARBON 4.7 5% 1/4W F	
R708	1-249-417-11	CARBON 1K 5% 1/6W		R765	1-249-455-11	CARBON 4.7 5% 1/4W F	
R709	1-249-417-11	CARBON 1K 5% 1/6W		R766	1-247-833-00	CARBON 1.2K 5% 1/6W	
R710	1-214-909-00	METAL 68K 1% 1/2W		R767	1-249-420-11	CARBON 1.8K 5% 1/6W	
R711	1-214-909-00	METAL 68K 1% 1/2W		R768	1-216-449-11	METAL OXIDE 56 5% 2W F	
R712	1-214-909-00	METAL 68K 1% 1/2W		R769	1-217-403-00	FUSIBLE 220 5% 1/4W F	
R713	1-247-839-00	CARBON 2.2K 5% 1/6W		VARIABLE RESISTOR			
R714	1-237-839-00	CARBON 2.2K 5% 1/6W		RV701	1-230-105-00	RES, ADJ, CARBON 3.3K	
R715	1-249-423-11	CARBON 3.3K 5% 1/6W		RV702	1-230-103-00	RES, ADJ, CARBON 2.2K	
R716	1-249-429-11	CARBON 10K 5% 1/6W		RV741	1-230-641-11	RES, ADJ, METAL GLAZE 2.2M	
R717	1-249-429-11	CARBON 10K 5% 1/6W		SPARK GAP			
R718	1-249-429-11	CARBON 10K 5% 1/6W		S6701	1-519-063-XX	DISCHARGING GAP	
R719	1-249-425-11	CARBON 4.7K 5% 1/6W		S6702	1-519-063-XX	DISCHARGING GAP	
R720	1-249-420-11	CARBON 1.8K 5% 1/6W					

D

D

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
L304	1-408-602-21	MICRO INDUCTOR 8.2UH		RESISTOR				R054	1-247-815-00	CARBON	220 5% 1/6W	R279	1-217-387-00	FUSIBLE	10 5% 1/4W F
L306	1-410-260-11	MICRO INDUCTOR 33UH		R001	1-249-417-11	CARBON	1K 5% 1/6W	R056	1-247-865-00	CARBON	15K 5% 1/6W	R280	1-249-417-11	CARBON	100K 5% 1/6W
L307	1-410-261-11	MICRO INDUCTOR 5.6UH		R002	1-249-417-11	CARBON	1K 5% 1/6W	R057	1-249-429-11	CARBON	10K 5% 1/6W	R281	1-247-849-00	CARBON	5.6K 5% 1/6W
L308	1-408-415-00	MICRO INDUCTOR 33UH		R003	1-249-417-11	CARBON	1K 5% 1/6W	R060	1-247-819-00	CARBON	330 5% 1/6W	R282	1-249-425-11	CARBON	4.7K 5% 1/6W
L310	1-407-705-00	MICRO INDUCTOR 100UH		R004	1-247-815-00	CARBON	220 5% 1/6W	R061	1-249-433-11	CARBON	22K 5% 1/6W	R283	1-247-713-11	CARBON	1K 5% 1/4W
L311	1-408-227-00	MICRO INDUCTOR 470UH		R005	1-247-815-00	CARBON	220 5% 1/6W	R201	1-247-710-11	CARBON	560 5% 1/4W	R284	1-247-700-11	CARBON	100 5% 1/4W F
L801	1-407-365-00	COIL, CHOKE		R006	1-247-815-00	CARBON	220 5% 1/6W	R202	1-247-710-11	CARBON	560 5% 1/4W	R285	1-249-425-11	CARBON	4.7K 5% 1/6W
L802	1-459-585-11	COIL (WITH CORE) (DRUM TYPE)		R007	1-247-815-00	CARBON	220 5% 1/6W	R203	1-247-721-11	CARBON	4.7K 5% 1/4W	R286	1-247-849-00	CARBON	5.6K 5% 1/6W
L803	1-459-224-00	H.C		R008	1-247-815-00	CARBON	220 5% 1/6W	R204	1-247-721-11	CARBON	4.7K 5% 1/4W	R287	1-249-441-11	CARBON	100K 5% 1/6W
L804	1-421-390-00	COIL, FERRITE (PMC)		R009	1-247-815-00	CARBON	220 5% 1/6W	R205	1-247-153-00	CARBON	8.2K 5% 1/4W	R288	1-247-713-11	CARBON	120K 5% 1/6W
L805	1-408-239-00	MICRO INDUCTOR 4.7MMH		R010	1-247-815-00	CARBON	220 5% 1/6W	R206	1-247-869-00	CARBON	39K 5% 1/6W	R289	1-249-437-11	CARBON	47K 5% 1/6W
L806	1-421-329-00	COIL, CHOKE		R011	1-247-815-00	CARBON	220 5% 1/6W	R207	1-247-719-11	CARBON	3.3K 5% 1/4W	R297	1-247-823-00	CARBON	470 5% 1/6W
L808	1-407-365-00	COIL, CHOKE		R012	1-247-799-00	CARBON	47 5% 1/6W	R208	1-249-423-11	CARBON	3.3K 5% 1/6W	R298	1-247-823-00	CARBON	470 5% 1/6W
L809	1-437-090-00	HOT		R013	1-247-815-00	CARBON	220 5% 1/6W	R209	1-249-429-11	CARBON	10K 5% 1/6W	R301	1-247-135-00	CARBON	1.5K 5% 1/4W
L810	1-407-365-00	COIL, CHOKE		R014	1-249-425-11	CARBON	4.7K 5% 1/6W	R210	1-249-419-11	CARBON	10K 5% 1/6W	R302	1-249-419-11	CARBON	1.5K 5% 1/6W
L811	1-459-074-00	COIL, DUST CORE 6.8MMH(HCC)		R015	1-249-425-11	CARBON	4.7K 5% 1/6W	R211	1-247-135-00	CARBON	1.5K 5% 1/4W	R303	1-247-816-00	CARBON	240 5% 1/6W
TRANSISTOR				R016	1-247-721-11	CARBON	4.7K 5% 1/4W	R213	1-247-895-00	CARBON	470K 5% 1/6W	R304	1-249-429-11	CARBON	10K 5% 1/6W
Q001	8-729-117-54	TRANSISTOR 2SA1175		R017	1-247-713-11	CARBON	1K 5% 1/4W	R214	1-249-419-11	CARBON	1.5K 5% 1/6W	R305	1-247-849-00	CARBON	470 5% 1/6W
Q003	8-729-178-54	TRANSISTOR 2SC2785		R018	1-249-417-11	CARBON	1K 5% 1/6W	R216	1-249-429-11	CARBON	10K 5% 1/6W	R306	1-247-823-00	CARBON	470 5% 1/6W
Q004	8-729-178-54	TRANSISTOR 2SC2785		R020	1-249-437-11	CARBON	47K 5% 1/6W	R217	1-249-417-11	CARBON	1K 5% 1/6W	R307	1-249-415-11	CARBON	680 5% 1/6W
Q006	8-729-178-54	TRANSISTOR 2SC2785		R021	1-247-859-00	CARBON	15K 5% 1/6W	R218	1-247-887-00	CARBON	220K 5% 1/6W	R308	1-249-425-11	CARBON	4.7K 5% 1/6W
Q007	8-729-603-50	TRANSISTOR 2SC403SP		R022	1-247-859-00	CARBON	15K 5% 1/6W	R219	1-247-887-00	CARBON	220K 5% 1/6W	R319	1-247-713-11	CARBON	1K 5% 1/4W
Q008	8-729-178-54	TRANSISTOR 2SC2785		R023	1-249-405-11	CARBON	100 5% 1/6W	R220	1-247-104-00	CARBON	75 5% 1/4W	R323	1-249-420-11	CARBON	1.8K 5% 1/6W
Q009	8-729-178-54	TRANSISTOR 2SC2785		R024	1-249-417-11	CARBON	1K 5% 1/6W	R221	1-247-708-11	CARBON	470 5% 1/4W	R324	1-249-414-11	CARBON	560 5% 1/6W
Q011	8-729-178-54	TRANSISTOR 2SC2785		R025	1-249-433-11	CARBON	22K 5% 1/6W	R222	1-247-873-00	CARBON	56K 5% 1/6W	R325	1-247-707-11	CARBON	390 5% 1/4W
Q201	8-729-178-54	TRANSISTOR 2SC2785		R026	1-247-859-00	CARBON	15K 5% 1/6W	R228	1-247-873-00	CARBON	56K 5% 1/6W	R326	1-249-440-11	CARBON	82K 5% 1/6W
Q206	8-729-178-54	TRANSISTOR 2SC2785		R027	1-247-708-11	CARBON	470 5% 1/4W	R229	1-249-422-11	CARBON	2.7K 5% 1/6W	R332	1-249-414-11	CARBON	560 5% 1/6W
Q207	8-729-117-54	TRANSISTOR 2SA1175		R028	1-247-163-00	CARBON	22K 5% 1/4W	R230	1-249-417-11	CARBON	1K 5% 1/6W	R333	1-247-849-00	CARBON	5.6K 5% 1/6W
Q208	8-729-117-54	TRANSISTOR 2SA1175		R029	1-249-433-11	CARBON	22K 5% 1/4W	R231	1-247-821-00	CARBON	390 5% 1/6W	R334	1-247-151-00	CARBON	6.8K 5% 1/4W
Q301	8-729-178-54	TRANSISTOR 2SC2785		R030	1-247-163-00	CARBON	22K 5% 1/4W	R232	1-247-688-11	CARBON	10 5% 1/4W	R335	1-249-437-11	CARBON	47K 5% 1/6W
Q305	8-729-178-54	TRANSISTOR 2SC2785		R031	1-247-163-00	CARBON	22K 5% 1/4W	R233	1-247-823-00	CARBON	470 5% 1/6W	R336	1-249-429-11	CARBON	10K 5% 1/6W
Q309	8-729-178-54	TRANSISTOR 2SC2785		R032	1-249-433-11	CARBON	22K 5% 1/6W	R234	1-249-440-11	CARBON	82K 5% 1/6W	R337	1-249-429-11	CARBON	10K 5% 1/6W
Q310	8-729-178-54	TRANSISTOR 2SC2785		R033	1-249-433-11	CARBON	22K 5% 1/6W	R235	1-247-903-00	CARBON	1M 5% 1/6W	R338	1-249-417-11	CARBON	1K 5% 1/6W
Q311	8-729-178-54	TRANSISTOR 2SC2785		R034	1-249-433-11	CARBON	22K 5% 1/6W	R236	1-249-429-11	CARBON	10K 5% 1/6W	R339	1-249-417-11	CARBON	1K 5% 1/6W
Q312	8-729-178-54	TRANSISTOR 2SC2785		R035	1-249-433-11	CARBON	22K 5% 1/6W	R237	1-247-839-00	CARBON	2.2K 5% 1/6W	R340	1-247-821-00	CARBON	390 5% 1/6W
Q313	8-729-178-54	TRANSISTOR 2SC2785		R037	1-249-417-11	CARBON	1K 5% 1/6W	R238	1-249-420-11	CARBON	1.8K 5% 1/6W	R341	1-247-821-00	CARBON	390 5% 1/6W
Q320	8-729-603-50	TRANSISTOR 2SC403SP		R038	1-249-422-11	CARBON	2.7K 5% 1/6W	R239	1-247-839-00	CARBON	2.2K 5% 1/6W	R342	1-247-903-00	CARBON	1M 5% 1/6W
Q502	8-729-117-54	TRANSISTOR 2SA1175		R039	1-249-405-11	CARBON	100 5% 1/6W	R240	1-249-429-11	CARBON	10K 5% 1/6W	R343	1-249-441-11	CARBON	100K 5% 1/6W
Q504	8-729-117-54	TRANSISTOR 2SA1175		R040	1-249-433-11	CARBON	22K 5% 1/6W	R242	1-249-429-11	CARBON	10K 5% 1/6W	R344	1-247-149-00	CARBON	5.6K 5% 1/4W
Q505	8-729-168-82	TRANSISTOR 2SC2688		R041	1-249-435-11	CARBON	33K 5% 1/6W	R243	1-249-432-11	CARBON	18K 5% 1/6W	R345	1-247-882-00	CARBON	130K 5% 1/6W
Q506	8-729-169-02	TRANSISTOR 2SC2690A		R042	1-247-823-00	CARBON	470 5% 1/6W	R244	1-249-460-11	CARBON	15K 5% 1/4W	R347	1-249-414-11	CARBON	560 5% 1/6W
Q507	8-729-122-02	TRANSISTOR 2SA1220A		R043	1-247-823-00	CARBON	470 5% 1/6W	R245	1-249-437-11	CARBON	47K 5% 1/6W	R348	1-249-415-11	CARBON	680 5% 1/6W
Q508	8-729-195-82	TRANSISTOR 2SC2958		R044	1-249-417-11	CARBON	1K 5% 1/6W	R247	1-247-137-00	CARBON	1.8K 5% 1/4W	R349	1-247-849-00	CARBON	5.6K 5% 1/6W
Q510	8-729-178-54	TRANSISTOR 2SC2785		R045	1-247-713-11	CARBON	1K 5% 1/4W	R248	1-247-713-11	CARBON	1K 5% 1/4W	R350	1-247-853-00	CARBON	8.2K 5% 1/6W
Q511	8-729-178-54	TRANSISTOR 2SC2785		R046	1-249-425-11	CARBON	4.7K 5% 1/6W	R249	1-247-137-00	CARBON	1.8K 5% 1/4W	R351	1-249-433-11	CARBON	22K 5% 1/6W
Q512	8-729-900-36	TRANSISTOR DTC124ES		R047	1-249-405-11	CARBON	100 5% 1/6W	R251	1-247-815-00	CARBON	220 5% 1/6W	R352	1-249-420-11	CARBON	1.8K 5% 1/6W
Q514	8-729-178-54	TRANSISTOR 2SC2785		R048	1-249-441-11	CARBON	100K 5% 1/6W	R252	1-249-405-11	CARBON	100 5% 1/6W	R353	1-249-423-11	CARBON	3.3K 5% 1/6W
Q515	8-729-178-54	TRANSISTOR 2SC2785		R049	1-216-464-11	METAL OXIDE	18K 5% 2W F	R253	1-249-405-11	CARBON	100 5% 1/6W	R354	1-247-883-00	CARBON	150K 5% 1/6W
Q551	8-729-177-43	TRANSISTOR 2SD174		R050	1-217-387-00	FUSIBLE	10 5% 1/4W F	R254	1-249-405-11	CARBON	100 5% 1/6W	R356	1-247-857-00	CARBON	12K 5% 1/6W
Q552	8-729-374-02	TRANSISTOR 2SB740		R052	1-247-713-11	CARBON	1K 5% 1/4W	R255	1-247-719-11	CARBON	3.3K 5% 1/4W	R357	1-247-849-00	CARBON	5.6K 5% 1/6W
Q802	8-729-300-90	TRANSISTOR 2SD1497-06		R053	1-247-883-00	CARBON	150K 5% 1/6W	R256	1-247-719-11	CARBON	3.3K 5% 1/4W	R358	1-249-432-11	CARBON	18K 5% 1/6W
Q803	8-719-801-06	THYRISTOR S6344G						R257	1-247-104-00	CARBON	75 5% 1/4W	R359	1-247-859-00	CARBON	15K 5% 1/6W
								R278	1-217-387-00	FUSIBLE	10 5% 1/4W F	R360	1-246-517-00	CARBON	68K 5% 1/4W

D

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
C315	1-123-381-00	ELECT	2.2MF	20%	50V		
C316	1-108-622-91	MYLAR	0.0047MF	10%	100V		
C317	1-108-630-91	MYLAR	0.022MF	10%	100V		
C318	1-131-345-00	TANTALUM	0.47MF	10%	35V		
C319	1-123-356-00	ELECT	10MF	20%	16V		
C320	1-123-586-00	ELECT	0.1MF	20%	50V		
C321	1-131-345-00	TANTALUM	0.47MF	10%	35V		
C322	1-131-345-00	TANTALUM	0.47MF	10%	35V		
C323	1-102-110-00	CERAMIC	220PF	10%	50V		
C324	1-102-110-00	CERAMIC	220PF	10%	50V		
C325	1-136-173-00	FILM	0.47MF	5%	50V		
C326	1-136-173-00	FILM	0.47MF	5%	50V		
C327	1-121-705-00	ELECT	2.2MF	30%	25V		
C328	1-102-973-00	CERAMIC	100PF	5%	50V		
C329	1-101-004-00	CERAMIC	0.01MF		50V		
C331	1-161-330-00	CERAMIC	0.01MF	30%	25V		
C332	1-101-880-00	CERAMIC	47PF	5%	50V		
C333	1-123-356-00	ELECT	10MF	20%	16V		
C334	1-123-356-00	ELECT	10MF	20%	16V		
C336	1-102-858-00	CERAMIC	10PF	0.5PF	50V		
C337	1-102-888-00	CERAMIC	150PF	5%	50V		
C338	1-102-884-00	CERAMIC	33PF	5%	50V		
C339	1-102-959-00	CERAMIC	22PF	5%	50V		
C340	1-102-945-00	CERAMIC	8PF	1PF	50V		
C341	1-102-947-00	CERAMIC	10PF	5%	50V		
C342	1-102-676-00	CERAMIC	68PF	5%	50V		
C343	1-102-973-00	CERAMIC	100PF	5%	50V		
C344	1-123-379-00	ELECT	0.47MF	20%	50V		
C346	1-123-333-00	ELECT	100MF	20%	16V		
C347	1-108-622-91	MYLAR	0.0047MF	10%	100V		
C348	1-123-379-00	ELECT	0.47MF	20%	50V		
C350	1-123-318-00	ELECT	33MF	20%	16V		
C501	1-108-630-91	MYLAR	0.022MF	10%	100V		
C502	1-136-171-00	FILM	0.33MF	5%	50V		
C503	1-136-171-00	FILM	0.33MF	5%	50V		
C504	1-102-108-00	CERAMIC	150PF	10%	50V		
C505	1-123-380-00	ELECT	1MF	20%	50V		
C506	1-123-330-00	ELECT	22MF	20%	16V		
C507	1-106-224-00	MYLAR	0.15MF	10%	100V		
C508	1-123-356-00	ELECT	10MF	20%	16V		
C509	1-123-369-00	ELECT	4.7MF	20%	25V		
C510	1-123-323-00	ELECT	470MF	20%	16V		
C511	1-123-379-00	ELECT	0.47MF	20%	50V		
C512	1-106-220-00	MYLAR	0.1MF	10%	100V		
C513	1-130-023-00	FILM	0.0027MF	5%	50V		
C514	1-123-332-00	ELECT	47MF	20%	16V		
C515	1-106-220-00	MYLAR	0.1MF	10%	100V		
C516	1-123-357-00	ELECT	22MF	20%	50V		
C517	1-102-030-00	CERAMIC	330PF	10%	500V		
C518	1-129-743-00	FILM	0.022MF	10%	400V		
C519	1-123-931-00	ELECT	3.3MF	20%	160V		
C520	1-106-182-00	MYLAR	0.0027MF	10%	100V		
C521	1-102-157-00	CERAMIC	560PF	10%	500V		
C522	1-123-318-00	ELECT	33MF	20%	16V		
C523	1-108-431-00	MYLAR	0.068MF	10%	200V		
C524	1-123-162-00	ELECT	1MF	20%	50V		
C525	1-123-362-00	ELECT	330MF	20%	50V		
C527	1-123-360-00	ELECT	100MF	20%	50V		
C528	1-123-321-00	ELECT	220MF	20%	16V		
C529	1-123-333-00	ELECT	100MF	20%	16V		
C530	1-106-359-00	MYLAR	0.0047MF	10%	200V		
C531	1-123-356-00	ELECT	10MF	20%	50V		
C532	1-106-190-00	MYLAR	0.0056MF	10%	100V		
C540	1-108-614-91	MYLAR	0.001MF	10%	100V		
C543	1-123-360-00	ELECT	100MF	20%	50V		
C545	1-123-379-00	ELECT	0.47MF	20%	50V		
C546	1-123-380-00	ELECT	1MF	20%	50V		
C551	1-123-322-00	ELECT	330MF	20%	16V		
C552	1-123-333-00	ELECT	100MF	20%	16V		
C553	1-123-333-00	ELECT	100MF	20%	16V		
C801	1-123-093-00	ELECT	22MF	20%	160V		
C802	1-102-157-00	CERAMIC	560PF	10%	500V		
C803	1-102-327-11	CERAMIC	330PF	15%	1.5KV		
C804	1-161-754-11	CERAMIC	0.001MF	10%	3KV		
C805	1-108-423-00	MYLAR	0.015MF	10%	200V		
C806	1-129-721-00	FILM	0.039MF	10%	630V		
C807	1-136-117-00	FILM	2MF	5%	200V		
C808	1-136-053-00	FILM	1.2MF	5%	200V		
C809	1-108-845-00	MYLAR	0.047MF	10%	50V		
C810	1-106-196-00	MYLAR	0.01MF	10%	100V		
C811	1-106-212-00	MYLAR	0.047MF	10%	100V		
C812	1-102-223-00	CERAMIC	0.0047MF	10%	2KV		
C813	1-106-210-00	MYLAR	0.039MF	10%	100V		
C814	1-123-949-00	ELECT	33MF	20%	250V		
C815	1-123-362-00	ELECT	330MF	20%	50V		
C816	1-102-030-00	CERAMIC	330PF	10%	500V		
C818	1-130-894-00	FILM	0.022MF	3%	1.2KV		
C819	1-129-711-51	FILM	0.0056MF	10%	630V		
C821	1-102-038-00	CERAMIC	0.001MF		500V		
C822	1-102-038-00	CERAMIC	0.001MF		500V		
C824	1-108-630-91	MYLAR	0.022MF	10%	100V		
C825	1-136-184-00	MYLAR	0.68MF	10%	250V		
C828	1-102-114-00	CERAMIC	470PF	10%	50V		
C830	1-123-380-00	ELECT	1MF	20%	50V		
CF001	1-527-790-00	OSCILLATOR, CERAMIC					
CN201	1-561-534-00	SOCKET, PIN 21P					
CN202	1-536-813-21	TERMINAL BOARD, INPUT/OUTPUT					
CN251	1-536-813-21	TERMINAL BOARD, INPUT/OUTPUT					
CN252	1-536-813-21	TERMINAL BOARD, INPUT/OUTPUT					
D1	*1-560-288-00	PLUG, CONNECTOR (2.5MM PITCH)					
D3	*1-564-880-31	PLUG, CONNECTOR 3P					

D

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
D4	*1-564-885-11	PLUG, CONNECTOR 8P		D223	8-719-101-76	D100E RD10E-L2	
D5	*1-508-765-00	3P PLUG (M)		D224	8-719-101-76	D100E RD10E-L2	
D6	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P		D271	8-719-911-55	D100E U05G	
D7	*1-564-883-11	PLUG, CONNECTOR 6P		D303	8-719-911-19	D100E 1SS119	
D8	*1-564-889-11	PLUG, CONNECTOR 12P		D304	8-719-911-19	D100E 1SS119	
D10	*1-508-766-00	4P PLUG (M)		D305	8-719-911-19	D100E 1SS119	
D12	*1-508-786-00	2P PLUG (M)		D306	8-719-911-19	D100E 1SS119	
D14	*1-564-884-31	PLUG, CONNECTOR 7P		D307	8-719-911-19	D100E 1SS119	
D15	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D308	8-719-911-19	D100E 1SS119	
D16	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D309	8-719-911-19	D100E 1SS119	
D17	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		D312	8-719-911-19	D100E 1SS119	
D18	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P		D501	8-719-911-19	D100E 1SS119	
D19	*1-564-346-00	CONNECTOR, BOARD TO BOARD 18P		D503	8-719-924-06	D100E ERC24-06S	
D20	*1-564-346-00	CONNECTOR, BOARD TO BOARD 18P		D504	8-719-924-06	D100E ERC24-06S	
D21	*1-560-123-00	PLUG, CONNECTOR (2.5MM PITCH)		D505	8-719-924-06	D100E ERC24-06S	
D22	*1-560-127-00	PLUG, CONNECTOR (2.5MM PITCH)		D506	8-719-911-19	D100E 1SS119	
D23	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)		D507	8-719-924-06	D100E ERC24-06S	
D24	*1-508-784-00	1P PLUG		D551	8-719-911-19	D100E 1SS119	
D27	*1-560-290-00	PLUG, CONNECTOR (2.5MM PITCH)		D552	8-719-911-19	D100E 1SS119	
D28	*1-508-784-00	1P PLUG		D553	8-719-924-06	D100E ERC24-06S	
D30	*1-564-879-11	PLUG, CONNECTOR 2P		D554	8-719-924-06	D100E ERC24-06S	
D32	*1-508-784-00	1P PLUG		D555	8-719-911-19	D100E 1SS119	
DY1	*1-508-765-00	3P PLUG (M)		D801	8-719-900-26	D100E ERD29-08J	
DY2	*1-508-765-00	3P PLUG (M)		D802	8-719-300-65	D100E ES1F	
DY3	*1-508-766-00	4P PLUG (M)		D803	8-719-924-06	D100E ERC24-06S	
CV301	1-141-181-11	CAP, TRIMMER		D804	8-719-924-06	D100E ERC24-06S	
		TRIMMER		D805	8-719-931-13	D100E EQ801-13	
		DIODE		D806	8-719-305-15	D100E GH3F	
				D807	8-719-305-15	D100E GH3F	
						DELAY LINE	
0001	8-719-911-19	D100E 1SS119		DL301	1-415-427-11	DELAY LINE, Y	
0002	8-719-911-19	D100E 1SS119		DL302	1-415-122-31	DELAY LINE, 1H (PAL)	
0003	8-719-911-19	D100E 1SS119				IC	
0004	8-719-911-19	D100E 1SS119 (KV-27XSC ONLY)		IC001	8-759-603-67	IC CX523-117P	
0005	8-759-157-40	IC UPC574J		IC002	8-759-600-92	IC M58657P	
0006	8-719-100-98	D100E RD30E-B2		IC201	8-759-914-76	IC CX20199	
0008	8-719-911-19	D100E 1SS119		IC202	8-752-006-10	IC CX20061	
0010	8-719-911-19	D100E 1SS119		IC251	8-749-943-62	IC STK-4362	
0061	8-719-100-35	D100E R05.6E-B2			*4-368-684-01	SPRING (L);IC251	
0062	8-719-911-19	D100E 1SS119		IC301	8-759-927-67	IC TDA3562A-N5	
D201	8-719-911-19	D100E 1SS119		IC551	8-759-915-46	IC TDA2579	
D205	8-719-100-44	D100E RD7.5E-B2			4-375-717-01	HEAT SINK, IC;IC551	
D206	8-719-911-19	D100E 1SS119				MODULE	
D212	8-719-911-19	D100E 1SS119		IC302	1-235-534-11	CONTROL MODULE, PICTURE	
D213	8-719-911-19	D100E 1SS119				COIL	
D214	8-719-911-19	D100E 1SS119		L001	1-408-425-00	MICRO INDUCTOR 220UH	
D215	8-719-911-19	D100E 1SS119		L251	1-459-407-00	COIL, FERRITE CHOKE	
D216	8-719-911-19	D100E 1SS119		L252	1-459-407-00	COIL, FERRITE CHOKE	
D217	8-719-911-19	D100E 1SS119		L301	1-404-495-00	COIL	
D218	8-719-911-19	D100E 1SS119		L302	1-408-412-00	MICRO INDUCTOR 18UH	
D219	8-719-911-19	D100E 1SS119					
D221	8-719-101-76	D100E RD10E-L2					
D222	8-719-101-76	D100E RD10E-L2					

H2

(KV27XSTA only)

Ref.No. Part No. Description Remark

DIODE

LED401 8-719-908-08 DIODE SL-1274
 *1-526-638-00 SOCKET, IC (9P); LED401
 LED402 8-719-903-11 DIODE GL-9PR24
 LED404 8-719-903-11 DIODE GL-9PR24
 LED405 8-719-903-11 DIODE GL-9PR24
 LED406 8-719-903-11 DIODE GL-9PR24

RESISTOR

R407 1-247-813-00 CARBON 180 5% 1/6W
 R412 1-247-813-00 CARBON 180 5% 1/6W

MISCELLANEOUS

1-246-521-00 RES, CARBON 100K
 A 1-451-255-31 DEFLECTION YOKE (SY-164)
 1-452-032-00 MAGNET, DISK; 10MM Ø
 1-452-094-00 MAGNET, ROTATABLE DISK; 15MM Ø
 1-452-146-21 MAGNET, BMC
 A 1-452-391-21 NECK ASSY, CRT (NA305)
 A 1-536-817-31 TERMINAL BOARD ASSY, ANTENNA
 A 1-551-270-11 CORD, POWER
 L901 A 1-426-278-11 COIL, DEMAGNETIZATION
 RV901 A 1-228-544-11 RESISTOR ASSY, HIGH-VOLTAGE
 RV902 A 1-237-280-11 RESISTOR ASSY, HIGH-VOLTAGE
 S901 A 1-554-762-41 SWITCH, PUSH (AC POWER)(1 KEY)
 SP901 1-503-642-11 SPEAKER (R)
 SP902 1-503-642-11 SPEAKER (L)
 V901 A 8-736-653-05 CRT (A64JKJ60X)

ACCESSORIES AND PACKING MATERIALS

Part No.	Description	Remark
A-1470-758-A	COMMANDER ASSY (RM-635)	
3-701-627-00	BAG, POLYETHYLENE	
4-337-844-00	BAG, PROTECTION	
4-482-288-41	MANUAL, INSTRUCTION	

*A-1296-105-A A BOARD, SUB COMPLETE

*4-368-692-03 CASE (MAIN), SHIELD
 *4-368-693-02 CASE (UPPER LID), SHIELD

Num. Ref.	Num. Parte	Description	Osservazione	Num. Ref.	Num. Parte	Descrizione	Osservazione
*4-368-694-02 CASE (BOTTOM LID), SHIELD				C151	1-101-004-00	CERAMIC 0.01MF	50V
CONNECTOR				C152	1-101-004-00	CERAMIC 0.01MF	50V
A1	*1-564-880-31	PLUG, CONNECTOR 3P		C153	1-123-356-00	ELECT 10MF	20% 16V
A2	*1-560-126-00	PLUG, CONNECTOR (2.5MM) 6P		C154	1-101-004-00	CERAMIC 0.01MF	50V
A3	*1-564-889-11	PLUG, CONNECTOR 12P		C155	1-123-332-00	ELECT 47MF	20% 16V
CAPACITOR				C156	1-123-306-00	ELECT 47MF	20% 10V
C102	1-123-356-00	ELECT 10MF	20% 16V	C157	1-123-306-00	ELECT 47MF	20% 10V
C104	1-123-356-00	ELECT 10MF	20% 16V	C158	1-123-379-00	ELECT 0.47MF	20% 50V
C105	1-123-356-00	ELECT 10MF	20% 16V	C159	1-102-816-00	CERAMIC 120PF	5% 50V
C106	1-123-323-00	ELECT 470MF	20% 16V	C160	1-102-125-00	CERAMIC 0.0047MF	10% 50V
C107	1-123-330-00	ELECT 22MF	20% 16V	C164	1-108-620-91	MYLAR 0.0033MF	10% 100V
C108	1-136-163-00	FILM 0.068MF	5% 50V	C165	1-108-620-91	MYLAR 0.0033MF	10% 100V
C109	1-136-163-00	FILM 0.068MF	5% 50V	C167	1-108-620-91	MYLAR 0.0033MF	10% 100V
C110	1-102-963-00	CERAMIC 33PF	5% 50V	C168	1-108-620-91	MYLAR 0.0033MF	10% 100V
C111	1-123-318-00	ELECT 33MF	20% 16V	C169	1-123-356-00	ELECT 10MF	20% 16V
C112	1-102-527-00	CERAMIC 82PF	5% 50V	C170	1-123-356-00	ELECT 10MF	20% 16V
C113	1-102-510-00	CERAMIC 12PF	5% 50V	C171	1-123-318-00	ELECT 33MF	20% 16V
C115	1-102-852-00	CERAMIC 47PF	5% 50V	C172	1-123-379-00	ELECT 0.47MF	20% 50V
C116	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C173	1-123-379-00	ELECT 0.47MF	20% 50V
C117	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C174	1-110-190-81	MYLAR 0.01MF	10% 400V
C118	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C175	1-110-190-81	MYLAR 0.01MF	10% 400V
C119	1-108-603-00	MYLAR 0.1MF	5% 50V	C176	1-123-380-00	ELECT 1MF	20% 50V
C120	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C177	1-123-380-00	ELECT 1MF	20% 50V
C122	1-123-330-00	ELECT 22MF	20% 16V	C179	1-123-369-00	ELECT 4.7MF	20% 25V
C123	1-102-108-00	CERAMIC 150PF	10% 50V	C180	1-108-620-91	MYLAR 0.0033MF	10% 100V
C124	1-104-069-00	POLYSTYRENE 470PF	5% 50V	C181	1-123-318-00	ELECT 33MF	20% 16V
C125	1-101-361-00	CERAMIC 150PF	5% 50V	C182	1-123-307-00	ELECT 100MF	20% 10V
C126	1-123-318-00	ELECT 33MF	20% 16V	C183	1-101-361-00	CERAMIC 150PF	5% 50V
C127	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C184	1-102-973-00	CERAMIC 100PF	5% 50V
C128	1-101-004-00	CERAMIC 0.01MF	50V	C186	1-102-121-00	CERAMIC 0.0022MF	10% 50V
C129	1-101-004-00	CERAMIC 0.01MF	50V	C188	1-102-125-00	CERAMIC 0.0047MF	10% 50V
C130	1-102-125-00	CERAMIC 0.0047MF	10% 50V	C189	1-101-006-00	CERAMIC 0.047MF	50V
C131	1-123-381-00	ELECT 2.2MF	20% 50V	C190	1-106-220-00	MYLAR 0.1MF	10% 100V
C132	1-102-125-00	CERAMIC 0.0047MF	10% 50V	FILTER			
C133	1-102-125-00	CERAMIC 0.0047MF	10% 50V	CD151	1-404-501-00	DISCRIMINATOR, CERAMIC	
C134	1-102-125-00	CERAMIC 0.0047MF	10% 50V	CF101	1-527-840-00	FILTER, CERAMIC	
C135	1-102-525-00	CERAMIC 68PF	5% 50V	CF102	1-404-134-00	TRAP, CERAMIC (5.5MHZ)	
C136	1-102-525-00	CERAMIC 68PF	5% 50V	CF151	1-527-839-00	FILTER, CERAMIC	
C137	1-102-125-00	CERAMIC 0.0047MF	10% 50V	DIODE			
C138	1-123-380-00	ELECT 1MF	20% 50V	D102	8-719-911-19	DIODE 1SS119	
C139	1-102-125-00	CERAMIC 0.0047MF	10% 50V	D103	8-719-102-71	DIODE R05.6E-N2	
C140	1-102-125-00	CERAMIC 0.0047MF	10% 50V	D104	8-719-911-19	DIODE 1SS119	
C141	1-123-318-00	ELECT 33MF	20% 16V	D105	8-719-911-19	DIODE 1SS119	
C142	1-102-525-00	CERAMIC 68PF	5% 50V	D151	8-719-911-19	DIODE 1SS119	
C143	1-101-004-00	CERAMIC 0.01MF	50V	D152	8-719-911-19	DIODE 1SS119	
C144	1-123-286-00	ELECT 0.33MF	20% 50V	D153	8-719-911-19	DIODE 1SS119	
C145	1-102-961-00	CERAMIC 27PF	5% 50V	D154	8-719-911-19	DIODE 1SS119	
C146	1-123-380-00	ELECT 1MF	20% 50V	D170	8-719-911-19	DIODE 1SS119	
C147	1-130-072-00	FILM 0.022MF	2% 100V	D171	8-719-911-19	DIODE 1SS119	
C148	1-110-186-81	MYLAR 0.0047MF	10% 400V				
C150	1-102-520-00	CERAMIC 39PF	5% 50V				

D

D

J1

H1

H2

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
R362	1-247-717-11	CARBON 2.2K 5% 1/4W		R537	1-249-441-11	CARBON 100K 5% 1/6W	
R364	1-247-839-00	CARBON 2.2K 5% 1/6W		R538	1-247-753-11	CARBON 1.2K 5% 1/2W F	
R365	1-247-857-00	CARBON 12K 5% 1/6W		R539	1-249-440-11	CARBON 82K 5% 1/6W	
R366	1-247-717-11	CARBON 2.2K 5% 1/4W		R540	1-246-507-00	CARBON 27K 5% 1/4W	
R367	1-247-815-00	CARBON 220 5% 1/6W		R541	1-247-823-00	CARBON 470 5% 1/6W	
R368	1-247-815-00	CARBON 220 5% 1/6W		R542	1-216-435-11	METAL OXIDE 2.7K 5% 1W F	
R369	1-247-815-00	CARBON 220 5% 1/6W		R543	1-247-903-00	CARBON 1M 5% 1/6W	
R370	1-247-708-11	CARBON 470 5% 1/4W		R544	1-202-467-92	SOL ID 3.3M 10% 1/4W	
R371	1-249-405-11	CARBON 100 5% 1/6W		R547	1-212-990-00	FUSIBLE 220 5% 1/2W F	
R373	1-247-713-11	CARBON 1K 5% 1/4W		R548	1-216-350-11	METAL OXIDE 1.2 5% 1W F	
R376	1-246-507-00	CARBON 27K 5% 1/4W		R549	1-247-033-00	CARBON 100 5% 1/8W F	
R377	1-246-507-00	CARBON 27K 5% 1/4W		R550	1-246-537-00	CARBON 470K 5% 1/4W F	
R378	1-249-432-11	CARBON 18K 5% 1/6W		R551	1-217-383-00	FUSIBLE 4.7 5% 1/4W F	
R379	1-247-864-00	CARBON 24K 5% 1/6W		R552	1-217-383-00	FUSIBLE 4.7 5% 1/4W F	
R380	1-249-440-11	CARBON 82K 5% 1/6W		R553	1-246-979-00	CARBON 1.2 5% 1/8W F	
R381	1-249-417-11	CARBON 1K 5% 1/6W		R554	1-249-425-11	CARBON 4.7K 5% 1/6W	
R382	1-249-417-11	CARBON 1K 5% 1/6W		R555	1-247-839-00	CARBON 2.2K 5% 1/6W	
R383	1-249-417-11	CARBON 1K 5% 1/6W		R556	1-216-350-11	METAL OXIDE 1.2 5% 1W F	
R385	1-249-422-11	CARBON 2.7K 5% 1/6W		R557	1-247-819-00	CARBON 330 5% 1/6W	
R386	1-249-422-11	CARBON 2.7K 5% 1/6W		R558	1-247-883-00	CARBON 150K 5% 1/6W	
R387	1-249-422-11	CARBON 2.7K 5% 1/6W		R559	1-247-719-11	CARBON 3.3K 5% 1/4W	
R390	1-247-161-00	CARBON 18K 5% 1/4W		R560	1-247-839-00	CARBON 2.2K 5% 1/6W	
R504	1-249-422-11	CARBON 2.7K 5% 1/6W		R571	1-247-895-00	CARBON 470K 5% 1/6W	
R505	1-249-423-11	CARBON 3.3K 5% 1/6W		R572	1-249-441-11	CARBON 100K 5% 1/6W	
R506	1-247-833-00	CARBON 1.2K 5% 1/6W		R573	1-247-903-00	CARBON 1M 5% 1/6W	
R507	1-249-417-11	CARBON 1K 5% 1/6W		R574	1-247-903-00	CARBON 1M 5% 1/6W	
R508	1-215-461-00	METAL 47K 1% 1/6W		R575	1-247-177-00	CARBON 82K 5% 1/4W	
R509	1-215-477-00	METAL 220K 1% 1/6W		R578	1-247-704-11	CARBON 220 5% 1/4W	
R510	1-247-851-00	CARBON 6.8K 5% 1/6W		R593	1-249-425-11	CARBON 4.7K 5% 1/6W	
R511	1-247-805-00	CARBON 82 5% 1/6W		R594	1-249-433-11	CARBON 22K 5% 1/6W	
R512	1-247-829-00	CARBON 820 5% 1/6W		R595	1-247-859-00	CARBON 15K 5% 1/6W	
R513	1-247-857-00	CARBON 12K 5% 1/6W		R596	1-249-423-11	CARBON 3.3K 5% 1/6W	
R514	1-249-417-11	CARBON 1K 5% 1/6W		R597	1-247-719-11	CARBON 3.3K 5% 1/4W	
R515	1-247-700-11	CARBON 100 5% 1/4W		R598	1-247-849-00	CARBON 5.6K 5% 1/6W	
R516	1-247-717-11	CARBON 2.2K 5% 1/4W		R599	1-247-815-00	CARBON 220 5% 1/6W	
R517	1-246-511-00	CARBON 39K 5% 1/4W		R800	1-215-886-11	METAL OXIDE 100 5% 2W F	
R520	1-214-765-00	METAL 33K 1% 1/4W		R801	1-216-345-11	METAL OXIDE 0.47 5% 1W F	
R521	1-216-464-11	METAL OXIDE 18K 5% 2W F		R802	1-247-137-00	CARBON 1.8K 5% 1/4W	
R522	1-247-901-00	CARBON 820K 5% 1/6W		R803	1-247-803-00	CARBON 68 5% 1/6W	
R523	1-247-033-00	CARBON 100 5% 1/8W F		R804	1-215-871-11	METAL OXIDE 2.2K 5% 1W F	
R524	1-215-869-11	METAL OXIDE 1K 5% 1W F		R805	1-215-866-11	METAL OXIDE 330 5% 1W F	
R525	1-246-985-00	CARBON 33 5% 1/8W F		R806	1-202-838-00	SOL ID 100K 10% 1/2W	
R526	1-247-839-00	CARBON 2.2K 5% 1/6W		R807	1-202-824-00	SOL ID 3.3K 10% 1/2W	
R527	1-246-982-00	CARBON 10 5% 1/8W F		R808	1-202-826-00	SOL ID 4.7K 10% 1/2W	
R528	1-247-161-00	CARBON 18K 5% 1/4W		R809	1-244-925-00	CARBON 150K 5% 1/2W	
R529	1-247-711-11	CARBON 680 5% 1/4W		R810	1-246-979-00	CARBON 1.2 5% 1/8W F	
R530	1-247-892-00	CARBON 360K 5% 1/6W		R811	1-249-448-11	CARBON 1.2 5% 1/4W F	
R531	1-247-707-11	CARBON 390 5% 1/4W		R812	1-247-270-00	CARBON 18K 5% 1/2W	
R532	1-247-719-11	CARBON 3.3K 5% 1/4W		R813	1-215-883-11	METAL OXIDE 33 5% 2W F	
R533	1-247-859-00	CARBON 15K 5% 1/6W		R814	1-246-537-00	CARBON 470K 5% 1/4W	
R534	1-247-787-00	CARBON 15 5% 1/6W		R817	1-216-379-11	METAL OXIDE 6.8 5% 2W F	
R535	1-247-783-00	CARBON 10 5% 1/6W		R820	1-215-884-11	METAL OXIDE 47 5% 2W F	
R536	1-216-354-11	METAL OXIDE 2.7 5% 1W F		R821	1-215-870-11	METAL OXIDE 1.5K 5% 1W F	

Ref.No.	Part No.	Description	Remark	Ref.No.	Part No.	Description	Remark
R825	1-207-678-00	WIREWOUND 10 10% 5W F				DIODE	
R826	1-207-678-00	WIREWOUND 10 10% 5W F		D401	8-719-911-19	DIODE 1SS119	
		VARIABLE RESISTOR		D402	8-719-911-19	DIODE 1SS119	
RV301	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K		D403	8-719-911-19	DIODE 1SS119	
RV302	1-228-724-00	RES, ADJ, CERAMIC CARBON 10K		D404	8-719-911-19	DIODE 1SS119	
RV303	1-228-725-00	RES, ADJ, CERAMIC CARBON 22K		D405	8-719-911-19	DIODE 1SS119	
RV501	1-226-776-00	RES, ADJ, METAL GLAZE 220K		D406	8-719-911-19	DIODE 1SS119	
RV502	1-226-775-00	RES, ADJ, METAL GLAZE 100K		D407	8-719-911-19	DIODE 1SS119	
RV503	1-230-522-11	RES, ADJ, METAL GLAZE 4.7K		D409	8-719-911-19	DIODE 1SS119	
RV558	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K				CONNECTOR	
RV558	1-228-720-00	RES, ADJ, CERAMIC CARBON 1K		H4	*1-564-457-11	PLUG, CONNECTOR (2.5MM) 9P	
		SPARK GAP		H5	*1-564-454-31	PLUG, CONNECTOR (2.5MM) 6P	
SG801	1-519-063-XX	DISCHARGING GAP		H6	*1-564-897-11	PLUG, CONNECTOR 8P	
		TRANSFORMER				RESISTOR	
T301	1-426-121-00	DAT		R401	1-249-425-11	CARBON 4.7K 5% 1/6W	
T801	1-437-090-11	HOT		R402	1-249-425-11	CARBON 4.7K 5% 1/6W	
T802	1-439-332-42	TRANSFORMER ASSY, FLYBACK		R405	1-247-849-00	CARBON 5.6K 5% 1/6W	
T803	1-413-059-00	TRANSFORMER, FERRITE (DFT)		R406	1-247-849-00	CARBON 5.6K 5% 1/6W	
		THERMISTOR		R418	1-247-839-00	CARBON 2.2K 5% 1/6W	
TH501	1-806-213-00	THERMISTOR		R419	1-249-420-11	CARBON 1.8K 5% 1/6W	
		CRYSTAL				VARIABLE RESISTOR	
X301	1-527-789-00	VINRATOR, CRYSTAL		RV401	1-228-578-00	RES, VAR, CARBON 10K	
		*****		RV402	1-228-578-00	RES, VAR, CARBON 10K	
		*1-618-883-11 J1 BOARD		RV403	1-228-578-00	RES, VAR, CARBON 10K	
		*****		RV404	1-228-578-00	RES, VAR, CARBON 10K	
		CONNECTOR				SWITCH	
CN901	1-507-657-00	JACK (LARGE TYPE)		SW401	1-554-118-00	SWITCH, PUSH (1 KEY)	
J1	*1-564-883-11	PLUG, CONNECTOR 6P		SW407	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		RESISTOR		SW408	1-553-329-00	SWITCH, PUSH (MONO KEY)	
R901	1-247-708-11	CARBON 470 5% 1/4W		SW411	1-553-329-00	SWITCH, PUSH (MONO KEY)	
R902	1-247-708-11	CARBON 470 5% 1/4W		SW412	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****		SW413	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*1-619-358-11 H1 BOARD		SW414	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****		SW415	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*1-506-908-11 PLUG, CONNECTOR (2.5MM) 14P		SW416	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		CAPACITOR		SW417	1-553-329-00	SWITCH, PUSH (MONO KEY)	
C401	1-123-617-00	ELECT 10MF 20% 16V		SW418	1-553-329-00	SWITCH, PUSH (MONO KEY)	
C403	1-123-616-00	ELECT 4.7MF 20% 25V		SW419	1-553-329-00	SWITCH, PUSH (MONO KEY)	
		*****				*****	
		*1-506-908-11 PLUG, CONNECTOR (2.5MM) 14P				*1-619-359-11 H2 BOARD	
		*4-373-201-01 COVER, LED HOLDER				*****	
		*4-373-202-01 HOLDER, LED					

(KV27XSTA only)

*A-1325-030-A V BOARD, COMPLETE

*4-371-102-01 CASE (MAIN), SHIELD, AI
*4-371-103-01 CASE (UPPER LID), SHIELD, AI
*4-371-104-01 CASE (BOTTOM LID), SHIELD, AI

CAPACITOR

C001	1-123-307-00	ELECT	100MF	20%	10V
C002	1-123-332-00	ELECT	47MF	20%	16V
C003	1-123-309-00	ELECT	330MF	20%	6.3V
C004	1-123-332-00	ELECT	47MF	20%	16V
C005	1-123-308-00	ELECT	220MF	20%	6.3V
C006	1-123-321-00	ELECT	220MF	20%	16V
C007	1-110-175-81	MYLAR	0.1MF	10%	100V
C008	1-102-951-00	CERAMIC	15PF	5%	50V
C009	1-102-074-00	CERAMIC	0.001MF	10%	50V
C010	1-102-824-00	CERAMIC	470PF	5%	50V
C011	1-110-182-81	MYLAR	0.022MF	10%	250V
C012	1-102-980-00	CERAMIC	270PF	5%	50V
C013	1-102-973-00	CERAMIC	100PF	5%	50V
C014	1-102-851-00	CERAMIC	15PF	5%	50V
C015	1-102-883-00	CERAMIC	27PF	5%	50V
C016	1-110-190-81	MYLAR	0.01MF	10%	400V
C017	1-110-171-81	MYLAR	0.047MF	10%	100V
C018	1-102-953-00	CERAMIC	18PF	5%	50V
C019	1-110-171-81	MYLAR	0.047MF	10%	100V
C020	1-102-978-00	CERAMIC	220PF	5%	50V
C021	1-110-173-81	MYLAR	0.068MF	10%	100V
C022	1-102-963-00	CERAMIC	33PF	5%	50V
C023	1-102-963-00	CERAMIC	33PF	5%	50V
C024	1-136-177-00	FILM	1MF	5%	50V
C025	1-123-298-00	ELECT	470MF	20%	6.3V



Num. Ref.	Num. Parte	Descrizione	Osservazione
C026	1-102-973-00	CERAMIC 100PF	5% 50V
C037	1-110-175-81	MYLAR 0.1MF	10% 100V
C040	1-136-177-00	FILM 1MF	5% 50V
C041	1-110-175-81	MYLAR 0.1MF	10% 100V
C042	1-102-820-00	CERAMIC 330PF	5% 50V
C043	1-123-308-00	ELECT 220MF	20% 6.3V
C044	1-110-175-81	MYLAR 0.1MF	10% 100V
C045	1-102-116-00	CERAMIC 680PF	10% 50V
C046	1-123-356-00	ELECT 10MF	20% 16V
C049	1-101-361-00	CERAMIC 150PF	10% 50V
C050	1-101-361-00	CERAMIC 150PF	10% 50V
TRIMMER			
CT001	1-141-181-11	CAP, TRIMMER	
DIODE			
D001	8-719-911-19	DIODE 1SS119	
D002	8-719-100-35	DIODE RU5.6E-82	
D003	8-719-100-68	DIODE RU13E-82	
D004	8-719-101-41	DIODE RU13.9E-42	
D005	8-719-109-88	DIODE RU5.6ES-81	
D006	8-719-911-19	DIODE 1SS119	
D007	8-719-911-19	DIODE 1SS119	
D008	8-719-911-19	DIODE 1SS119	
D011	8-719-911-19	DIODE 1SS119	
D012	8-719-911-19	DIODE 1SS119	
D013	8-719-109-88	DIODE RU5.6ES-81	
IC			
IC001	8-759-918-54	IC SAA5230	
IC002	8-759-924-41	IC SAA5240B	
	*1-526-722-00	SOCKET, IC 40P; IC002	
IC003	8-759-206-27	IC TC5564PL-15	
IC004	8-759-108-76	IC CX526-050	
COIL			
L001	1-408-411-00	MICRO INDUCTOR 15UH	
TRANSISTOR			
Q001	8-729-109-53	TRANSISTOR 2SD1795A	
Q002	8-729-178-54	TRANSISTOR 2SC2785	
Q003	8-729-177-43	TRANSISTOR 2SD1774	
Q004	8-729-117-54	TRANSISTOR 2SA1175	
Q005	8-729-900-89	TRANSISTOR DTC144ES	
Q006	8-729-117-54	TRANSISTOR 2SA1175	
Q007	8-729-178-54	TRANSISTOR 2SC2785	
Q008	8-729-178-54	TRANSISTOR 2SC2785	
Q009	8-729-900-89	TRANSISTOR DTC144ES	
Q010	8-729-117-54	TRANSISTOR 2SA1175	
Q011	8-729-117-54	TRANSISTOR 2SA1175	
Q012	8-729-117-54	TRANSISTOR 2SA1175	



Num. Ref.	Num. Parte	Descrizione	Osservazione	Num. Ref.	Num. Parte	Descrizione	Osservazione
RESISTOR							
R001	1-215-867-00	METAL OXIDE	470 5% 1W F	X002	1-567-495-11	OSCILLATOR, CRYSTAL	
R002	1-215-762-91	METAL	10K 5% 1/6W	X003	1-567-192-11	OSCILLATOR, CERAMIC	
R003	1-215-778-91	METAL	47K 5% 1/6W	*****			
R004	1-247-745-11	CARBON	330 5% 1/2W				
R005	1-215-736-91	METAL	820 5% 1/6W				
R006	1-215-754-91	METAL	4.7K 5% 1/6W				
R007	1-215-726-91	METAL	330 5% 1/6W				
R008	1-215-780-91	METAL	56K 5% 1/6W				
R009	1-215-738-91	METAL	1K 5% 1/6W				
R010	1-215-770-91	METAL	22K 5% 1/6W				
R011	1-215-738-91	METAL	1K 5% 1/6W				
R012	1-215-762-91	METAL	10K 5% 1/6W				
R014	1-215-738-91	METAL	1K 5% 1/6W				
R015	1-215-738-91	METAL	1K 5% 1/6W				
R016	1-215-132-00	METAL	150 5% 1/4W				
R017	1-215-132-00	METAL	150 5% 1/4W				
R018	1-215-132-00	METAL	150 5% 1/4W				
R019	1-215-132-00	METAL	150 5% 1/4W				
R020	1-215-716-91	METAL	120 5% 1/6W				
R021	1-215-716-91	METAL	120 5% 1/6W				
R022	1-215-716-91	METAL	120 5% 1/6W				
R023	1-215-776-91	METAL	39K 5% 1/6W				
R024	1-215-756-91	METAL	5.6K 5% 1/6W				
R025	1-215-746-91	METAL	2.2K 5% 1/6W				
R040	1-215-714-91	METAL	100 5% 1/6W				
R044	1-217-376-00	FUSIBLE	1.2 5% 1/4W F				
R046	1-215-726-91	METAL	330 5% 1/6W				
R047	1-215-762-91	METAL	10K 5% 1/6W				
R048	1-215-764-91	METAL	12K 5% 1/6W				
R049	1-215-690-91	METAL	10 5% 1/6W				
R052	1-215-738-91	METAL	1K 5% 1/6W				
R065	1-215-738-91	METAL	1K 5% 1/6W				
VARIABLE RESISTOR							
RV001	1-230-631-11	RES, ADJ, CARBON 22K					
RV002	1-224-247-XX	RES, ADJ, METAL GLAZE 100					
CONNECTOR							
V1	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V2	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V4	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V5	*1-560-124-00	PLUG, CONNECTOR (2.5MM PITCH)					
V6	*1-508-784-00	1P PLUG					
V9	*1-560-126-00	PLUG, CONNECTOR (2.5MM PITCH)					
V10	*1-508-784-00	1P PLUG					
V11	*1-560-124-00	PLUG, CONNECTOR (2.5MM) 4P					
V12	*1-560-123-00	PLUG, CONNECTOR (2.5MM) 3P					
V13	*1-560-127-00	PLUG, CONNECTOR (2.5MM) 7P					
CRYSTAL							
X001	1-567-162-00	OSCILLATOR, CRYSTAL					

A

(KV27XSTA only)

Num. Ref.	Num. Parte	Descrizione
-----------	------------	-------------

IC

IC101	8-759-909-08	IC TDA3541
IC102	8-759-909-54	IC TDA2546A
IC103	8-759-602-16	IC M54572L
IC151	8-759-007-54	IC TDA4940
IC152	8-759-007-55	IC TDA4944

COIL

L102	1-404-476-00	COIL, IF
L103	1-408-432-31	MICRO INDUCTOR 1.5UH
L104	1-408-406-00	MICRO INDUCTOR 5.6UH
L105	1-404-477-00	COIL, IF
L106	1-404-493-00	COIL
L107	1-404-493-00	COIL
L109	1-408-409-00	MICRO INDUCTOR 10UH
L110	1-408-406-00	MICRO INDUCTOR 5.6UH
L111	1-404-493-00	COIL
L113	1-408-226-00	MICRO INDUCTOR 82UH
L114	1-407-489-00	MICRO INDUCTOR 560UH
L115	1-408-405-00	MICRO INDUCTOR 4.7UH
L116	1-408-406-00	MICRO INDUCTOR 5.6UH
L117	1-408-428-00	MICRO INDUCTOR 390UH
L170	1-408-247-00	MICRO INDUCTOR 33MH
L171	1-408-408-00	MICRO INDUCTOR 8.2UH

TRANSISTOR

Q101	8-729-178-54	TRANSISTOR 2SC2785
Q102	8-729-105-47	TRANSISTOR 2SC2026-L
Q103	8-729-117-54	TRANSISTOR 2SA1175
Q104	8-729-900-36	TRANSISTOR DTC124ES
Q105	8-729-117-54	TRANSISTOR 2SA1175
Q151	8-729-178-54	TRANSISTOR 2SC2785
Q152	8-729-178-54	TRANSISTOR 2SC2785
Q153	8-729-178-54	TRANSISTOR 2SC2785
Q154	8-729-900-89	TRANSISTOR DTC144ES
Q155	8-729-178-54	TRANSISTOR 2SC2785
Q156	8-729-178-54	TRANSISTOR 2SC2785
Q157	8-729-900-89	TRANSISTOR DTC144ES
Q158	8-729-900-89	TRANSISTOR DTC144ES
Q172	8-729-117-54	TRANSISTOR 2SA1175
Q173	8-729-178-54	TRANSISTOR 2SC2785
Q174	8-729-178-54	TRANSISTOR 2SC2785
Q175	8-729-178-54	TRANSISTOR 2SC2785

RESISTOR

R101	1-215-738-91	METAL	1K	5%	1/6W
R102	1-215-738-91	METAL	1K	5%	1/6W
R105	1-215-762-91	METAL	10K	5%	1/6W
R106	1-215-750-91	METAL	3.3K	5%	1/6W
R107	1-215-750-91	METAL	3.3K	5%	1/6W
R108	1-215-798-91	METAL	330K	5%	1/6W
R109	1-215-746-91	METAL	2.2K	5%	1/6W

Osservazione	Num. Ref.	Num. Parte	Descrizione
--------------	-----------	------------	-------------

	R110	1-215-746-91	METAL	2.2K	5%	1/6W
	R111	1-215-754-91	METAL	4.7K	5%	1/6W
	R112	1-215-744-91	METAL	1.8K	5%	1/6W
	R113	1-215-752-91	METAL	3.9K	5%	1/6W
	R114	1-215-722-91	METAL	220	5%	1/6W
	R115	1-215-742-91	METAL	1.5K	5%	1/6W
	R116	1-215-730-91	METAL	470	5%	1/6W
	R117	1-215-710-91	METAL	68	5%	1/6W
	R118	1-215-724-91	METAL	270	5%	1/6W
	R119	1-215-730-91	METAL	470	5%	1/6W
	R120	1-215-778-91	METAL	47K	5%	1/6W
	R122	1-215-762-91	METAL	10K	5%	1/6W
	R125	1-215-736-91	METAL	820	5%	1/6W
	R126	1-215-736-91	METAL	820	5%	1/6W
	R127	1-215-736-91	METAL	820	5%	1/6W
	R131	1-215-778-91	METAL	47K	5%	1/6W
	R132	1-215-762-91	METAL	10K	5%	1/6W
	R134	1-215-782-91	METAL	68K	5%	1/6W
	R135	1-215-780-91	METAL	56K	5%	1/6W
	R136	1-215-770-91	METAL	22K	5%	1/6W
	R137	1-215-770-91	METAL	22K	5%	1/6W
	R140	1-215-738-91	METAL	1K	5%	1/6W
	R141	1-215-766-91	METAL	15K	5%	1/6W
	R142	1-215-786-91	METAL	100K	5%	1/6W
	R143	1-215-786-91	METAL	100K	5%	1/6W
	R144	1-215-752-91	METAL	3.9K	5%	1/6W
	R145	1-215-752-91	METAL	3.9K	5%	1/6W
	R146	1-215-754-91	METAL	4.7K	5%	1/6W
	R151	1-215-736-91	METAL	820	5%	1/6W
	R152	1-215-776-91	METAL	39K	5%	1/6W
	R153	1-215-728-91	METAL	390	5%	1/6W
	R154	1-215-714-91	METAL	100	5%	1/6W
	R155	1-215-770-91	METAL	22K	5%	1/6W
	R156	1-215-784-91	METAL	82K	5%	1/6W
	R157	1-215-754-91	METAL	4.7K	5%	1/6W
	R158	1-215-754-91	METAL	4.7K	5%	1/6W
	R159	1-215-754-91	METAL	4.7K	5%	1/6W
	R160	1-215-754-91	METAL	4.7K	5%	1/6W
	R161	1-215-738-91	METAL	1K	5%	1/6W
	R162	1-215-738-91	METAL	1K	5%	1/6W
	R166	1-215-750-91	METAL	3.3K	5%	1/6W
	R167	1-215-774-91	METAL	33K	5%	1/6W
	R168	1-215-770-91	METAL	22K	5%	1/6W
	R172	1-215-720-91	METAL	180	5%	1/6W
	R173	1-215-778-91	METAL	47K	5%	1/6W
	R174	1-215-796-91	METAL	270K	5%	1/6W
	R175	1-215-772-91	METAL	27K	5%	1/6W
	R176	1-215-738-91	METAL	1K	5%	1/6W
	R177	1-215-762-91	METAL	10K	5%	1/6W
	R178	1-215-762-91	METAL	10K	5%	1/6W
	R179	1-215-762-91	METAL	10K	5%	1/6W
	R180	1-215-738-91	METAL	1K	5%	1/6W
	R181	1-215-740-91	METAL	1.2K	5%	1/6W

Osservazione

Num. Ref.	Num. Parte	Descrizione
-----------	------------	-------------

R182	1-215-746-91	METAL	2.2K	5%	1/6W
R183	1-215-738-91	METAL	1K	5%	1/6W
R184	1-215-724-91	METAL	270	5%	1/6W
R185	1-215-726-91	METAL	330	5%	1/6W
R188	1-215-766-91	METAL	15K	5%	1/6W

R191	1-215-732-91	METAL	560	5%	1/6W
R192	1-215-732-91	METAL	560	5%	1/6W
R193	1-215-714-91	METAL	100	5%	1/6W

VARIABLE RESISTOR

RV101	1-228-727-00	RES, ADJ, CERAMIC CARBON 47K
RV151	1-228-726-00	RES, ADJ, CERAMIC CARBON 33K

FILTER

SWF101	1-404-438-00	FILTER, SAW
--------	--------------	-------------

TUNER

TU101A	1-463-411-21	TUNER, UHF/VHF ET (UV411/CEI)
--------	--------------	-------------------------------

RM-635

KV-27XSTC Chassis No. SCC-774D-A

Serial No. 3,004,101 and later

SUPPLEMENT

SUBJECT:MODIFICATION OF CIRCUIT

1. SCHEMATIC DIAGRAM




IC001 SAA5230 8-759-918-54

SAA5231 8-759-944-59

R008 METAL 56K 1-249-438-11

METAL 68K 1-249-439-11

MOUNTING DIAGRAM



ELECTRICAL PARTS LIST

Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
*A-1135-316-A SCM BOARD, COMPLETE				TRANSISTOR			
*1-562-370-21 CONNECTOR, BOARD TO BOARD 18P				Q1351	8-729-245-B3	TRANSISTOR 2SC245B	
CAPACITOR				Q1352	8-729-204-B3	TRANSISTOR 2SA1048GR	
C1351	1-104-069-00	POLYSTYRENE 470PF	5K 50V	Q1354	8-729-245-B3	TRANSISTOR 2SC245B	
C1352	1-101-880-00	CERAMIC 47PF	5K 50V	Q1356	8-729-204-B3	TRANSISTOR 2SA1048GR	
C1353	1-110-192-91	MYLAR 0.015MF	10K 400V	Q1357	8-729-245-B3	TRANSISTOR 2SC245B	
C1354	1-123-369-00	ELECT 4.7MF	20K 25V	Q1359	8-729-245-B3	TRANSISTOR 2SC245B	
C1355	1-102-074-00	CERAMIC 0.001MF	10K 50V	Q1360	8-729-245-B3	TRANSISTOR 2SC245B	
RESISTOR				R1351	1-215-738-91	METAL 1K 5K 1/6W	
C1356	1-123-380-00	ELECT 1MF	20K 50V	R1352	1-215-802-91	METAL 470K 5K 1/6W	
C1357	1-102-074-00	CERAMIC 0.001MF	10K 50V	R1353	1-215-778-91	METAL 47K 5K 1/6W	
C1358	1-110-182-81	MYLAR 0.022MF	10K 250V	R1354	1-215-706-91	METAL 47 5K 1/6W	
C1359	1-101-004-00	CERAMIC 0.01MF	50V	R1355	1-215-750-91	METAL 3.3K 5K 1/6W	
C1360	1-101-004-00	CERAMIC 0.01MF	50V	R1356	1-215-756-91	METAL 5.6K 5K 1/6W	
C1361	1-123-332-00	ELECT 47MF	20K 16V	R1357	1-215-748-91	METAL 2.7K 5K 1/6W	
C1362	1-102-953-00	CERAMIC 18PF	5K 50V	R1361	1-215-708-91	METAL 3.3K 5K 1/6W	
C1363	1-102-953-00	CERAMIC 18PF	5K 50V	R1364	1-215-746-91	METAL 2.2K 5K 1/6W	
C1364	1-102-074-00	CERAMIC 0.001MF	10K 50V	R1365	1-215-762-91	METAL 10K 5K 1/6W	
C1366	1-101-006-00	CERAMIC 0.047MF	50V	R1367	1-215-778-91	METAL 47K 5K 1/6W	
C1367	1-123-356-00	ELECT 10MF	20K 16V	R1368	1-215-738-91	METAL 1K 5K 1/6W	
C1368	1-102-965-00	CERAMIC 39PF	5K 50V	R1371	1-215-774-91	METAL 3.3K 5K 1/6W	
C1369	1-102-824-21	CERAMIC 470PF	5K 50V	R1372	1-215-716-91	METAL 12K 5K 1/6W	
C1370	1-110-175-81	MYLAR 0.1MF	10K 100V	R1373	1-215-738-91	METAL 1K 5K 1/6W	
C1371	1-110-175-81	MYLAR 0.1MF	10K 100V	R1374	1-215-746-91	METAL 2.2K 5K 1/6W	
C1372	1-102-736-00	CERAMIC 150PF	5K 50V	R1375	1-215-720-91	METAL 18K 5K 1/6W	
C1373	1-101-004-00	CERAMIC 0.01MF	50V	R1380	1-215-770-91	METAL 22K 5K 1/6W	
C1374	1-123-356-00	ELECT 10MF	20K 16V	R1382	1-215-158-00	METAL 1.8K 5K 1/4W	
C1375	1-123-318-00	ELECT 33MF	20K 16V	R1383	1-215-746-91	METAL 2.2K 5K 1/6W	
C1376	1-161-317-00	CERAMIC 330PF	10K 50V	R1384	1-215-752-91	METAL 3.9K 5K 1/6W	
C1378	1-110-182-81	MYLAR 0.022MF	10K 250V	R1385	1-215-738-91	METAL 1K 5K 1/6W	
DIODE				R1386	1-215-738-91	METAL 1K 5K 1/6W	
D1351	8-719-026-11	DIODE 1T261		R1387	1-215-200-00	METAL 100K 5K 1/4W	
D1355	8-719-911-19	DIODE 1SS119		R1388	1-215-786-91	METAL 100K 5K 1/6W	
IC				R1389	1-215-734-91	METAL 68K 5K 1/6W	
IC1351	8-759-922-68	IC TDA3590A-N8		R1390	1-215-734-91	METAL 68K 5K 1/6W	
COIL				R1393	1-215-782-91	METAL 68K 5K 1/6W	
L1351	1-404-497-00	COIL		R1394	1-215-754-91	METAL 4.7K 5K 1/8W	
L1352	1-404-496-00	COIL		VARIABLE RESISTOR			
L1353	1-408-408-00	MICRO INDUCTOR 8.2uH		RV1351	1-230-522-11	RES, ADJ, METAL GLAZE 4.7K	
L1354	1-404-498-00	COIL					

KV-27XSD

RM-635

AEP Model

Serial No. 3026001 and later

Chassis No. SCC-774B-A

January, 1987


No. 1

SUPPLEMENT

SUBJECT: SCM BOARD MODIFICATION

File this supplement with the service manual.

SCHEMATIC DIAGRAM



KV27XS-C/TC/D/XSTA

457